

Safety detection solutions

Emergency stop rope pull switches



XY2CJ range

Emergency stop rope pull switches with single anchor point ISO M20, Pg 13.5 and 1/2" NPT

Turnbuckle or quick tensioner, cable and end spring to be ordered separately (1)

Without pilot light

Cable length	Colors and materials	Reset	Supply voltage	Contact type	Cable anchor point	Reference	Weight kg	
≤ 20 m	Polyamide head Zamak red RAL 3000 body Treated steel cover	By pull button	—		1 1 NC + NO slow break	RH side or LH side	XY2CJS15 (2)	0.455
					2 — NC + NC slow break	RH side or LH side	XY2CJS17 (2)	0.455
					2 1 2 NC + 1 NO slow break	RH side or LH side	XY2CJS19 (2) (3)	0.455
≤ 30 m	Zamak red RAL 3000 head and body Treated steel cover	By pull button	—		1 1 NC + NO slow break	RH side	XY2CJR15 (2)	0.669
					2 — NC + NC slow break	RH side	XY2CJR17 (2)	0.669
					2 1 2 NC + 1 NO slow break	RH side	XY2CJR19 (2) (3)	0.669
					1 1 NC + NO slow break	LH side	XY2CJL15 (2)	0.669
					2 — NC + NC slow break	LH side	XY2CJL17 (2)	0.669
					2 1 2 NC + 1 NO slow break	LH side	XY2CJL19 (2) (3)	0.669



(1) See separate parts on [page 12](#).

(2) For ISO M20 tapped cable entry version, add H29 to the end of the selected reference.

For example: **XY2CJS15** becomes **XY2CJS15H29**.

(3) For 1/2" NPT tapped cable entry version, add H7 to the end of the selected reference.

For example: **XY2CJS19** becomes **XY2CJS19H7**.