

Specifications



Eaton 169365

Eaton DA1 Variable frequency drive, 240 V AC, 3-phase, 74 A, IP55, NEMA 12, FS5, Radio interference, Brake chopper

General specifications

PRODUCT NAME	Eaton DA1 Variable frequency drive
CATALOG NUMBER	169365
MODEL CODE	DA1-32072FB-B55C
EAN	4015081658121
PRODUCT LENGTH/DEPTH	270 mm
PRODUCT HEIGHT	540 mm
PRODUCT WIDTH	235 mm
PRODUCT WEIGHT	22.5 kg

IEC/EN 61800-3
Safety: EN 61800-5-1: 2003

CSA-C22.2 No. 14

CUL

DNV

IEC/EN61800-5

UkrSEPRO

UL

RoHS, ISO 9001

EAC

UL Category Control No.:

NMMS, NMMS7

UL 508C

UL File No.: E172143

RCM

Specification for general requirements: IEC/EN 61800-2

CE

Certified by UL for use in Canada

IEC/EN61800-3

UL report applies to both US and Canada

CERTIFICATIONS

CATALOG NOTES

The brake resistors are assigned based on the maximum rated power of the variable frequency drive. Additional brake



Powering Business Worldwide

Apparent power

APPARENT POWER AT 230 V 28.68 kVA

APPARENT POWER AT 240 V 29.93 kVA

Climatic environmental conditions

ALTITUDE Max. 1000 m
Above 1000 m with 1 %
derating per 100 m
Max. 4000 m

AMBIENT OPERATING TEMPERATURE - MAX 40 °C

AMBIENT STORAGE TEMPERATURE - MAX 60 °C

AMBIENT OPERATING TEMPERATURE - MIN -10 °C

AMBIENT OPERATING TEMPERATURE AT 150% OVERLOAD - MAX 40 °C

AMBIENT OPERATING TEMPERATURE AT 150% OVERLOAD - MIN -10 °C

AMBIENT STORAGE TEMPERATURE - MIN -40 °C

CLIMATIC PROOFING < 95 average relative
humidity (RH), no
condensation, no
corrosion

resistors and designs (e.g.
different duty cycles) are
available upon request.

Braking function

BRAKING RESISTANCE 12 Ω

BRAKING TORQUE Max. 100 % of rated
operational current I_e,
variable, DC - Main circuit
Max. 30 % MN, Standard -
Main circuit
Max. 100 % of rated
operational current I_e with
external braking resistor -
Main circuit

SWITCH-ON THRESHOLD FOR THE BRAKING TRANSISTOR 390 VDC

Control circuit

NUMBER OF INPUTS (ANALOG) 2

NUMBER OF INPUTS (DIGITAL) 5

NUMBER OF OUTPUTS (ANALOG) 2

NUMBER OF OUTPUTS (DIGITAL) 2

NUMBER OF RELAY OUTPUTS 2 (parameterizable, 1 N/O
and 1 changeover contact,
6 A (250 V, AC-1) / 5 A (30
V, DC-1))

RATED CONTROL VOLTAGE (UC) 24 V DC (external, max.
100 mA)

Design verification

10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION	Does not apply, since the

General information

CABLE LENGTH	C2 ≤ 5 m, Radio interference level, maximum motor cable length C3 ≤ 25 m, Radio interference level, maximum motor cable length 100 m, screened, maximum permissible, Motor feeder 300 m, unscreened, with motor choke, maximum permissible, Motor feeder 150 m, unscreened, maximum permissible, Motor feeder 200 m, screened, with motor choke, maximum permissible, Motor feeder
COMMUNICATION INTERFACE	Modbus RTU, built in OP-Bus (RS485), built in PROFINET, optional CANopen®, built in PROFIBUS, optional EtherCAT, optional DeviceNet, optional Modbus-TCP, optional SmartWire-DT, optional Ethernet IP, optional
CONNECTION TO SMARTWIRE-DT	Yes In conjunction with DX-NET-SWD1 SmartWire DT module
DEGREE OF PROTECTION	IP55 NEMA 12
ELECTROMAGNETIC COMPATIBILITY	1st and 2nd environments (according to EN 61800-3)
FITTED WITH:	Brake chopper Additional PCB protection OLED display DC link choke Internal DC link IGBT inverter Control unit Radio interference suppression filter Breaking resistance PC connection
FRAME SIZE	FS5
FUNCTIONS	4-quadrant operation possible
MOUNTING POSITION	Vertical
PRODUCT CATEGORY	Variable frequency drives

AGAINST ELECTRIC SHOCK	entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID	518 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID	0 W
RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)	72 A
STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS	0 W

PROTECTION	Finger and back-of-hand proof, Protection against direct contact (BGV A3, VBG4)
PROTOCOL	Other bus systems MODBUS PROFINET IO PROFIBUS CAN DeviceNet EtherNet/IP TCP/IP
RADIO INTERFERENCE CLASS	Optional external radio interference suppression filter for longer motor cable lengths and for use in different EMC environments C2, C3: depending on the motor cable length, the connected load, and ambient conditions. External radio interference suppression filters (optional) may be necessary.
SAFETY FUNCTION/LEVEL	STO (Safe Torque Off, SIL2, PLc Cat 2)
SUITABLE FOR	Branch circuits, (UL/CSA)

Main circuit

EFFICIENCY	97.2 % (η)
HEAT DISSIPATION AT CURRENT/SPEED	180 W at 25% current and 0% speed 240 W at 25% current and 50% speed 290 W at 50% current and 0% speed 370 W at 50% current and 50% speed 460 W at 50% current and 90% speed 550 W at 100% current and 0% speed 720 W at 100% current and 50% speed 900 W at 100% current and 90% speed
INPUT CURRENT ILN AT 150% OVERLOAD	74 A
LEAKAGE CURRENT AT GROUND IPE - MAX	0.28 mA
MAINS SWITCH-ON FREQUENCY	Maximum of one time every 30 seconds
MAINS VOLTAGE - MAX	240 V
MAINS VOLTAGE - MIN	200 V
OPERATING MODE	Sensorless vector control (SLV) Optional: Vector control with feedback (CLV) Speed control with slip compensation U/f control
OUTPUT FREQUENCY - MAX	500 Hz
OUTPUT FREQUENCY - MIN	0 Hz
OUTPUT VOLTAGE (U2)	230 V AC, 3-phase 240 V AC, 3-phase
OVERLOAD CURRENT IL AT 150% OVERLOAD	108 A
RATED CONTROL SUPPLY VOLTAGE	10 V DC (Us, max. 10 mA)
RATED FREQUENCY - MAX	62 Hz
RATED FREQUENCY - MIN	48 Hz
RATED OPERATIONAL CURRENT (IE) AT 150% OVERLOAD	72 A
RATED OPERATIONAL POWER AT 220/230 V, 50 HZ, 1-PHASE	18.5 kW

Motor rating

ASSIGNED MOTOR CURRENT IM AT 220 - 240 V, 60 HZ, 150% OVERLOAD	68 A
ASSIGNED MOTOR CURRENT IM AT 230 V, 50 HZ, 150% OVERLOAD	71 A
ASSIGNED MOTOR POWER AT 230/240 V, 60 HZ, 1-PHASE	25 HP

RATED OPERATIONAL VOLTAGE	240 V AC, 3-phase 230 V AC, 3-phase
RESOLUTION	0.1 Hz (Frequency resolution, setpoint value)
SHORT-CIRCUIT PROTECTION RATING	110 A, UL (Class CC or J), Safety device (fuse or miniature circuit-breaker), Power Wiring
STARTING CURRENT - MAX	200 %, IH, max. starting current (High Overload), for 4 seconds every 40 seconds, Power section
SUPPLY FREQUENCY	50/60 Hz
SWITCHING FREQUENCY	8 kHz, 4 - 24 kHz adjustable (audible), fPWM, Power section, Main circuit
SYSTEM CONFIGURATION TYPE	AC supply systems with earthed center point
VOLTAGE RATING - MAX	240 VAC

Resources

[eaton-powerxl-da1-dc1-de1-system-bus-ap040022-en-us.pdf](#)

[eaton-powerxl-da1-vector-control-induction-motors-ap040028-en-us.pdf](#)

[eaton-powerxl-da1-derating-ap040039-en-us.pdf](#)

[eaton-powerxl-da1-dc1-de1-conformal-coating-ap040182-en-us.pdf](#)

[Start, Stopp und Betrieb](#)

[eaton-powerxl-da1-dc1-de1-internal-motor-protection-ap040016-en-us.pdf](#)

[eaton-powerxl-da1-use-of-multiple-ramps-ap040031-en-us.pdf](#)

[eaton-powerxl-da1-i-o-configuration-ap040034-en-us.pdf](#)

APPLICATION NOTES

[eaton-powerxl-da1-hoist-applications-ap040032-en-us.pdf](#)

[eaton-powerxl-da1-dc1-db1-de1-rapidlink5-firmware-update-ap040214-en-us.pdf](#)

[eaton-powerxl-da1-pid-controller-ap040025-en-us.pdf](#)

[eaton-powerxl-da1-set-point-setting-ap040040-en-us.pdf](#)

[eaton-powerxl-da1-pointer-to-parameter-ap040133-en-us.pdf](#)

[eaton-powerxl-vfd-dual-rating-ap040114-en-us.pdf](#)

[Electromagnetic compatibility \(EMC\)](#)

[eaton-powerxl-da1-operating-pm-bldc-motors-ap040051-en-us.pdf](#)

	eaton-powerxl-dx-com-stick-3-ap040190-en-us.pdf eaton-powerxl-da1-motor-vf-curves-induction-motors-ap040018-en-us.pdf eaton-powerxl-da1-master-slave-operation-ap040026-en-us.pdf eaton-powerxl-da1-starting-stopping-operation-ap040030-en-us.pdf eaton-powerxl-da1-droop-function-ap040023-en-us.pdf
BROCHURES	eaton-powerxl-variable-frequency-drives-dc1-da1-brochure-br040001en-en-us.pdf
CATALOGUES	eaton-drives-soft-starter-catalog-ca04020001zen-us.pdf
DECLARATIONS OF CONFORMITY	eaton-variable-frequency-drive-declaration-of-conformity-eu250662en.pdf eaton-variable-frequency-drive-declaration-of-conformity-uk251145en.pdf
DRAWINGS	eaton-frequency-inverter-dimensions-024.eps eaton-frequency-inverter-3d-drawing-015.eps
ECAD MODEL	DA-CE-ETN.DA1-32072FB-B55C
INSTALLATION INSTRUCTIONS	eaton-da1-variable-frequency-drive-il04020011z.pdf
INSTALLATION VIDEOS	Video PowerXL DA1 PowerXL Variable Frequency Drives DC1 and DA1 - EN
MANUALS AND USER GUIDES	eaton-powerxl-da1-installation-manual-mn04020005z-en-us.pdf

	eaton-powerxl-da1-application-manual-mn04020006z-en-us.pdf MN040018_EN eaton-da1-variable-frequency-drive-mn040063-en-us.pdf eaton-powerxl-vfd-profinet-manual-mn040062en-us.pdf eaton-canopen-communication-manual-for-variable-frequency-drives-variable-speed-starters-da1-db1-dc1-de11-mn040019-en-us.pdf
MCAD MODEL	DA-CS-da1 fs5 ip55 eaton-general-purpose-drives-mcad-drawings-da1-fs5-ip55.dwg
MULTIMEDIA	System solutions based on EtherCAT Looking for variable frequency drives DC1 and DA1 which can be used in harsh environments?
PRODUCT NOTIFICATIONS	eaton-drives-ecodesign-directive-mz040046en-en.pdf
SOFTWARE, FIRMWARE, AND APPLICATIONS	eaton-powerxl-da1-ethercat-esi-for-omron-v311.zip eaton-powerxl-pcsoftware-drivesconnect-v1501.zip eaton-powerxl-da1-ethercat-esi-v310.zip eaton-powerxl-da1-profinet-gsdml-v226.zip eaton-powerxl-da1-canopen-eds-v250.zip eaton-powerxl-da1-swd-codesys-v3-library.zip eaton-powerxl-da1-ethernetip-eds-v150.zip eaton-powerxl-da1-devicenet-eds-v100.zip

[eaton-powerxl-da1-
canopen-codesys-v3-
library.zip](#)

[eaton-powerxl-da1-
firmware-release-note-
mz040041en-us.pdf](#)

[eaton-powerxl-dx-cbl-pc-
3m0-usb-driver.zip](#)

[eaton-powerxl-da1-
profibus-gsd-v216.zip](#)

[eaton-powerxl-dx-
comstick3-ble-drivers.zip](#)

[eaton-powerxl-dx-cbl-pc-
1m5-usb-driver.zip](#)

[eaton-powerxl-da1-
profinet-tia-v12-library.zip](#)

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



Eaton Corporation plc Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2026 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

