

Specifications



Eaton 169367

Eaton DA1 Variable frequency drive, 240 V AC, 3-phase, 99.1 A, IP55, NEMA 12, FS6, Radio interference, Brake chopper

General specifications

PRODUCT NAME	Eaton DA1 Variable frequency drive
CATALOG NUMBER	169367
MODEL CODE	DA1-32090FB-B55C
EAN	4015081658145
PRODUCT LENGTH/DEPTH	313.5 mm
PRODUCT HEIGHT	865 mm
PRODUCT WIDTH	330 mm
PRODUCT WEIGHT	50 kg

Safety: EN 61800-5-1: 2003

CERTIFICATIONS

UL 508C
UL report applies to both US and Canada
Certified by UL for use in Canada
IEC/EN61800-3
CE
IEC/EN61800-5
CUL
UL File No.: E172143
UL Category Control No.: NMMS, NMMS7
DNV
UL
EAC
RCM
CSA-C22.2 No. 14
UkrSEPRO
RoHS, ISO 9001
IEC/EN 61800-3
Specification for general requirements: IEC/EN 61800-2

CATALOG NOTES

The brake resistors are assigned based on the maximum rated power of the variable frequency drive. Additional brake



Powering Business Worldwide

Apparent power

APPARENT POWER AT 230 V	35.85 kVA
--------------------------------	-----------

APPARENT POWER AT 240 V	37.41 kVA
--------------------------------	-----------

Climatic environmental conditions

ALTITUDE	Above 1000 m with 1 % derating per 100 m Max. 4000 m Max. 1000 m
-----------------	--

AMBIENT OPERATING TEMPERATURE - MAX	40 °C
--	-------

AMBIENT STORAGE TEMPERATURE - MAX	60 °C
--	-------

AMBIENT OPERATING TEMPERATURE - MIN	-10 °C
--	--------

AMBIENT OPERATING TEMPERATURE AT 150% OVERLOAD - MAX	40 °C
---	-------

AMBIENT OPERATING TEMPERATURE AT 150% OVERLOAD - MIN	-10 °C
---	--------

AMBIENT STORAGE TEMPERATURE - MIN	-40 °C
--	--------

CLIMATIC PROOFING	< 95 average relative humidity (RH), no condensation, no corrosion
--------------------------	--

resistors and designs (e.g. different duty cycles) are available upon request.

Braking function

BRAKING RESISTANCE	6 Ω
---------------------------	-----

BRAKING TORQUE	Max. 30 % MN, Standard - Main circuit Max. 100 % of rated operational current I_e , variable, DC - Main circuit Max. 100 % of rated operational current I_e with external braking resistor - Main circuit
-----------------------	---

SWITCH-ON THRESHOLD FOR THE BRAKING TRANSISTOR	390 VDC
---	---------

Control circuit

NUMBER OF INPUTS (ANALOG)	2
----------------------------------	---

NUMBER OF INPUTS (DIGITAL)	5
-----------------------------------	---

NUMBER OF OUTPUTS (ANALOG)	2
-----------------------------------	---

NUMBER OF OUTPUTS (DIGITAL)	2
------------------------------------	---

NUMBER OF RELAY OUTPUTS	2 (parameterizable, 1 N/O and 1 changeover contact, 6 A (250 V, AC-1) / 5 A (30 V, DC-1))
--------------------------------	---

RATED CONTROL VOLTAGE (UC)	24 V DC (external, max. 100 mA)
-----------------------------------	---------------------------------

Design verification

10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION	Does not apply, since the

General information

CABLE LENGTH	150 m, unscreened, maximum permissible, Motor feeder 200 m, screened, with motor choke, maximum permissible, Motor feeder 300 m, unscreened, with motor choke, maximum permissible, Motor feeder C2 ≤ 5 m, Radio interference level, maximum motor cable length 100 m, screened, maximum permissible, Motor feeder C3 ≤ 25 m, Radio interference level, maximum motor cable length
COMMUNICATION INTERFACE	PROFIBUS, optional SmartWire-DT, optional PROFINET, optional CANopen®, built in Ethernet IP, optional Modbus RTU, built in EtherCAT, optional OP-Bus (RS485), built in DeviceNet, optional Modbus-TCP, optional
CONNECTION TO SMARTWIRE-DT	Yes In conjunction with DX-NET-SWD1 SmartWire DT module
DEGREE OF PROTECTION	IP55 NEMA 12
ELECTROMAGNETIC COMPATIBILITY	1st and 2nd environments (according to EN 61800-3)
FITTED WITH:	Radio interference suppression filter Additional PCB protection OLED display DC link choke IGBT inverter PC connection Control unit Brake chopper Internal DC link Breaking resistance
FRAME SIZE	FS6
FUNCTIONS	4-quadrant operation possible
MOUNTING POSITION	Vertical
PRODUCT CATEGORY	Variable frequency drives

AGAINST ELECTRIC SHOCK	entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID	550 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID	0 W
RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)	90 A
STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS	0 W

PROTECTION	Finger and back-of-hand proof, Protection against direct contact (BGV A3, VBG4)
PROTOCOL	PROFIBUS CAN MODBUS EtherNet/IP DeviceNet PROFINET IO Other bus systems TCP/IP
RADIO INTERFERENCE CLASS	C2, C3: depending on the motor cable length, the connected load, and ambient conditions. External radio interference suppression filters (optional) may be necessary. Optional external radio interference suppression filter for longer motor cable lengths and for use in different EMC environments
SAFETY FUNCTION/LEVEL	STO (Safe Torque Off, SIL2, PLc Cat 2)
SUITABLE FOR	Branch circuits, (UL/CSA)

Main circuit

EFFICIENCY	97.5 % (η)
HEAT DISSIPATION AT CURRENT/SPEED	240 W at 25% current and 50% speed 260 W at 25% current and 0% speed 300 W at 50% current and 0% speed 350 W at 50% current and 50% speed 440 W at 50% current and 90% speed 490 W at 100% current and 0% speed 600 W at 100% current and 50% speed 810 W at 100% current and 90% speed
INPUT CURRENT ILN AT 150% OVERLOAD	99.1 A
LEAKAGE CURRENT AT GROUND IPE - MAX	1.54 mA
MAINS SWITCH-ON FREQUENCY	Maximum of one time every 30 seconds
MAINS VOLTAGE - MAX	240 V
MAINS VOLTAGE - MIN	200 V
OPERATING MODE	Sensorless vector control (SLV) Speed control with slip compensation U/f control Optional: Vector control with feedback (CLV)
OUTPUT FREQUENCY - MAX	500 Hz
OUTPUT FREQUENCY - MIN	0 Hz
OUTPUT VOLTAGE (U2)	230 V AC, 3-phase 240 V AC, 3-phase
OVERLOAD CURRENT IL AT 150% OVERLOAD	135 A
RATED CONTROL SUPPLY VOLTAGE	10 V DC (Us, max. 10 mA)
RATED FREQUENCY - MAX	62 Hz
RATED FREQUENCY - MIN	48 Hz
RATED OPERATIONAL CURRENT (IE) AT 150% OVERLOAD	90 A
RATED OPERATIONAL POWER AT 220/230 V, 50 HZ, 1-PHASE	22 kW

Motor rating

ASSIGNED MOTOR CURRENT IM AT 220 - 240 V, 60 HZ, 150% OVERLOAD	80 A
ASSIGNED MOTOR CURRENT IM AT 230 V, 50 HZ, 150% OVERLOAD	71 A
ASSIGNED MOTOR POWER AT 230/240 V, 60 HZ, 1-PHASE	30 HP

RATED OPERATIONAL VOLTAGE	230 V AC, 3-phase 240 V AC, 3-phase
RESOLUTION	0.1 Hz (Frequency resolution, setpoint value)
SHORT-CIRCUIT PROTECTION RATING	150 A, UL (Class CC or J), Safety device (fuse or miniature circuit-breaker), Power Wiring
STARTING CURRENT - MAX	200 %, IH, max. starting current (High Overload), for 4 seconds every 40 seconds, Power section
SUPPLY FREQUENCY	50/60 Hz
SWITCHING FREQUENCY	4 kHz, 4 - 16 kHz adjustable (audible), fPWM, Power section, Main circuit
SYSTEM CONFIGURATION TYPE	AC supply systems with earthed center point
VOLTAGE RATING - MAX	240 VAC

Resources

[eaton-powerxl-da1-vector-control-induction-motors-ap040028-en-us.pdf](#)

[Electromagnetic compatibility \(EMC\)](#)

[eaton-powerxl-da1-derating-ap040039-en-us.pdf](#)

[eaton-powerxl-da1-dc1-de1-conformal-coating-ap040182-en-us.pdf](#)

[eaton-powerxl-da1-i-o-configuration-ap040034-en-us.pdf](#)

[eaton-powerxl-da1-set-point-setting-ap040040-en-us.pdf](#)

[eaton-powerxl-da1-pid-controller-ap040025-en-us.pdf](#)

[eaton-powerxl-da1-pointer-to-parameter-ap040133-en-us.pdf](#)

[eaton-powerxl-da1-dc1-de1-internal-motor-protection-ap040016-en-us.pdf](#)

[eaton-powerxl-da1-droop-function-ap040023-en-us.pdf](#)

[eaton-powerxl-da1-starting-stopping-operation-ap040030-en-us.pdf](#)

[Start, Stopp und Betrieb](#)

[eaton-powerxl-dx-com-stick-3-ap040190-en-us.pdf](#)

[eaton-powerxl-da1-operating-pm-bldc-motors-ap040051-en-us.pdf](#)

[eaton-powerxl-da1-master-slave-operation-ap040026-en-us.pdf](#)

APPLICATION NOTES

	eaton-powerxl-da1-motor-vf-curves-induction-motors-ap040018-en-us.pdf eaton-powerxl-da1-hoist-applications-ap040032-en-us.pdf eaton-powerxl-da1-use-of-multiple-ramps-ap040031-en-us.pdf eaton-powerxl-vfd-dual-rating-ap040114-en-us.pdf eaton-powerxl-da1-dc1-de1-system-bus-ap040022-en-us.pdf eaton-powerxl-da1-dc1-db1-de1-rapidlink5-firmware-update-ap040214-en-us.pdf
BROCHURES	eaton-powerxl-variable-frequency-drives-dc1-da1-brochure-br040001en-en-us.pdf
CATALOGUES	eaton-drives-soft-starter-catalog-ca04020001zen-us.pdf
DECLARATIONS OF CONFORMITY	eaton-variable-frequency-drive-declaration-of-conformity-eu250662en.pdf eaton-variable-frequency-drive-declaration-of-conformity-uk251145en.pdf
DRAWINGS	eaton-frequency-inverter-dimensions-025.eps eaton-frequency-inverter-3d-drawing-016.eps
ECAD MODEL	DA-CE-ETN.DA1-32090FB-B55C
INSTALLATION INSTRUCTIONS	eaton-da1-variable-frequency-drive-il04020011z.pdf
INSTALLATION VIDEOS	Video PowerXL DA1 PowerXL Variable Frequency Drives DC1 and DA1 - EN
MANUALS AND USER GUIDES	eaton-da1-variable-frequency-drive-mn040063-en-us.pdf

	eaton-powerxl-da1-application-manual-mn04020006z-en-us.pdf MN040018_EN eaton-canopen-communication-manual-for-variable-frequency-drives-variable-speed-starters-da1-db1-dc1-de11-mn040019-en-us.pdf eaton-powerxl-vfd-profinet-manual-mn040062en-us.pdf eaton-powerxl-da1-installation-manual-mn04020005z-en-us.pdf
MCAD MODEL	eaton-general-purpose-drives-mcad-drawings-da1-fs6.dwg DA-CS-da1_fs6
MULTIMEDIA	Looking for variable frequency drives DC1 and DA1 which can be used in harsh environments? System solutions based on EtherCAT
PRODUCT NOTIFICATIONS	eaton-drives-ecodesign-directive-mz040046en-en.pdf
SOFTWARE, FIRMWARE, AND APPLICATIONS	eaton-powerxl-da1-swd-codesys-v3-library.zip eaton-powerxl-dx-cbl-pc-3m0-usb-driver.zip eaton-powerxl-da1-profinet-gsdml-v226.zip eaton-powerxl-dx-cbl-pc-1m5-usb-driver.zip eaton-powerxl-dx-comstick3-ble-drivers.zip eaton-powerxl-da1-profinet-tia-v12-library.zip eaton-powerxl-da1-profibus-gsd-v216.zip eaton-powerxl-da1-canopen-eds-v250.zip eaton-powerxl-da1-devicenet-eds-v100.zip

[eaton-powerxl-da1-
canopen-codesys-v3-
library.zip](#)

[eaton-powerxl-da1-
firmware-release-note-
mz040041en-us.pdf](#)

[eaton-powerxl-da1-
ethercat-esi-v310.zip](#)

[eaton-powerxl-da1-
ethernetip-eds-v150.zip](#)

[eaton-powerxl-
pcsoftware-drivesconnect-
v1501.zip](#)

[eaton-powerxl-da1-
ethercat-esi-for-omron-
v311.zip](#)

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



Eaton Corporation plc Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2026 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

