

Specifications



Photo is representative



Eaton 171753

Eaton DS7 Soft starter, 160 A, 200 - 480 V AC, 24 V AC/DC, Frame size FS4, Ambient temperature Operation -40 - +40 °C

General specifications

PRODUCT NAME	Eaton DS7 Soft starter
---------------------	------------------------

CATALOG NUMBER	171753
-----------------------	--------

MODEL CODE	DS7-340SX160N0-L
-------------------	------------------

EAN	4015081680771
------------	---------------

PRODUCT LENGTH/DEPTH	178 mm
-----------------------------	--------

PRODUCT HEIGHT	215 mm
-----------------------	--------

PRODUCT WIDTH	105 mm
----------------------	--------

PRODUCT WEIGHT	3.799 kg
-----------------------	----------

CERTIFICATIONS

CSA-C22.2 No 14-05
GB 14048.6
CSA-C22.2 No 0-M91
UL 508
CSA File No.: 2511305
CSA22.2-14
C-Tick
UL
CSA
CSA Class No.: 321106
UL File No.: E251034
IEC/EN 60947-4-2
CE
UkrSEPRO

Ambient conditions, mechanical

MOUNTING POSITION	Vertical
SHOCK RESISTANCE	8 g, 11 ms, Mechanical
VIBRATION RESISTANCE	2M2 to EN 60721-3-2

Climatic environmental conditions

ALTITUDE	Above 1000 m with 1 % derating per 100 m Max. 2000 m
-----------------	--

AMBIENT OPERATING TEMPERATURE - MAX	40 °C
--	-------

AMBIENT STORAGE TEMPERATURE - MAX	60 °C
--	-------

AMBIENT OPERATING TEMPERATURE - MIN	-40 °C
--	--------

AMBIENT STORAGE TEMPERATURE - MIN	-40 °C
--	--------

CLIMATIC PROOFING	Damp heat, constant, to IEC 60068-2-3 Cold to EN 60068-2-1 Damp heat, cyclic, to IEC 60068-2-30
--------------------------	---

Control circuit

CURRENT CONSUMPTION	0,6 A/50 ms, Control circuit, Regulator supply at peak performance (close bypass) at 24 V DC 1.6 mA, Control circuit, Digital inputs, External 24 V 50 mA, Control circuit, Regulator supply
DROP-OUT TIME	350 ms, Control circuit, Digital Inputs, DC operated
DROP-OUT VOLTAGE	0 - 3 V, DC operated AC operated: 0 - 3 V, AC operated
PICK-UP TIME	250 ms at DC 250 ms at AC
PICK-UP VOLTAGE	17.3 - 27 V DC 17.3 - 27 V AC
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX	24 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	24 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	24 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN	24 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	24 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	24 V

Design verification

10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION	Does not apply, since the

AGAINST ELECTRIC SHOCK	entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID	30 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID	0 W
RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)	160 A
STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS	30 W

Features & functions

FITTED WITH:	Internal bypass Internal bypass contacts
FUNCTIONS	Suppression of closing transients Soft start function Potential isolation between power and control sections Min. ramp time 1 s - fast switching (semiconductor contactor) Suppression of DC components for motors Single direction

General information

CLASS	Other
CONNECTION TO SMARTWIRE-DT	No
DEGREE OF PROTECTION	IP20 NEMA 1
FRAME SIZE	FS4
MAINS VOLTAGE - MAX	480 V
MAINS VOLTAGE - MIN	200 V
OVERVOLTAGE CATEGORY	II
POLLUTION DEGREE	2
RADIO INTERFERENCE CLASS	Class B (EN 55011)
SUITABLE FOR	Branch circuits, (UL/CSA)

Input/Output

NUMBER OF OUTPUTS	2 Relay Outputs (TOR, Ready)
OUTPUT VOLTAGE	250 V AC (relay outputs)
PROTECTION	Finger and back-of-hand proof, Protection against direct contact
RATED CONTROL VOLTAGE (UC)	24 V DC (-15 %/+10 %) 24 V AC 24 V DC
RATED OPERATIONAL CURRENT (IE) AT AC-11	1 A

Motor rating

ASSIGNED MOTOR POWER AT 200/208 V, 60 HZ, 3-PHASE	50 HP
ASSIGNED MOTOR POWER AT 220/230 V, 60 HZ, 3-PHASE	60 HP
ASSIGNED MOTOR POWER AT 460/480 V, 60 HZ, 3-PHASE	125 HP
RATED OPERATIONAL POWER AT 220/230 V, 50 HZ	45 kW
RATED OPERATIONAL POWER AT 400 V, 50 HZ	90 kW

TYPE

Soft starter for three-phase loads

VOLTAGE TYPE

AC/DC

Main conducting paths

OVERLOAD CYCLE	AC-53a: 3 - 5: 75 - 10
RATED OPERATIONAL CURRENT (IE) AT AC-53	160 A
RATED OPERATIONAL VOLTAGE (UE) - MAX	480 V
RATED OPERATIONAL VOLTAGE (UE) - MIN	230 V
SHORT-CIRCUIT PROTECTION RATING	3 x 170M5008, Type „2“ coordination (additional with the fuses for coordination type „1“), Main conducting paths NZMN2-M200, Type “1” coordination, Main conducting paths
SUPPLY FREQUENCY	50/60 Hz, fLN, Main circuit
VOLTAGE RATING - MAX	480 V

Soft start function

APPLICATION	1-phase motors: No 3-phase motors: Yes - Soft starting of three-phase asynchronous motors
DELAY TIME	0 - 30 s, Soft start function, Ramp times
RAMP/RUN-UP TIME	30 s
START VOLTAGE	Min. 30 %, Soft start function, Start voltage = turn-off voltage Max. 100 %, Soft start function, Start voltage = turn-off voltage

Terminal capacities

SCREWDRIVER SIZE	0.6 x 3.5 mm, Terminal screws, Control circuit cables PZ2, 1 x 6 mm, Terminal screw, Standard screwdriver
TERMINAL CAPACITY (COPPER BAND)	2 x 9 x 0.8 mm, Main cables 10 x 16 x 0.8 mm, Main cables
TERMINAL CAPACITY (FLEXIBLE WITH FERRULE)	2 x (0.5 - 0.75) mm ² , Control circuit cables 1 x (0.5 - 1.5) mm ² , Control circuit cables
TERMINAL CAPACITY (SOLID)	2 x (0.5 - 1.0) mm ² , Control circuit cables 2 x (4 - 70) mm ² , Main cables 1 x (4 - 185) mm ² , Main cables 1 x (0.5 - 2.5) mm ² , Control circuit cables
TERMINAL CAPACITY (SOLID/STRANDED AWG)	2 x (12 - 00), Main cables 1 x (12 - 350 kcmil), Main cables 2 x (21 - 18), Control circuit cables 1 x (21 - 14), Control circuit cables
TERMINAL CAPACITY (STRANDED)	1 x (25 - 70) mm ² , Main cables 2 x (6 - 25) mm ² , Main cables 2 x (0.5 - 1.0) mm ² , Control circuit cables 1 x (0.5 - 1.5) mm ² , Control circuit cables
TIGHTENING TORQUE	6 Nm ($\leq$ 10 mm ²) 0.4 Nm, Screw terminals, Control circuit cables 9 Nm ($>$ 10 mm ²)

Resources

BROCHURES	eaton-softstarter-s811-ds7-brochure-br039001en-en-us.pdf
CATALOGUES	eaton-drives-soft-starter-catalog-ca04020001zen-us.pdf
DECLARATIONS OF CONFORMITY	eaton-soft-starter-declaration-of-conformity-eu250527en.pdf eaton-soft-starter-declaration-of-conformity-uk251010en.pdf
DRAWINGS	eaton-semiconductor-contactors-swd-ds7-soft-starter-dimensions.eps eaton-semiconductor-contactors-softstarter-ds7-3d-drawing-006.eps
ECAD MODEL	DA-CE-ETN.DS7-340SX160N0-L
INSTALLATION INSTRUCTIONS	IL03902005Z2021_06.pdf
MANUALS AND USER GUIDES	eaton-ds7-soft-starter-mn03901001z-en-us.pdf
MCAD MODEL	DA-CS-ds7_4_100316 eaton-soft-starters-mcad-drawings-ds7-4-100316.dwg
MULTIMEDIA	Soft starter DS7 up to 200 A

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
DATE:



Eaton Corporation plc Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2026 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

