

Specifications



Eaton 176970

Eaton DA1 Variable frequency drive, 600 V AC, 3-phase, 70.4 A, IP55, NEMA 12, FS5, Brake chopper

General specifications

PRODUCT NAME	Eaton DA1 Variable frequency drive
CATALOG NUMBER	176970
MODEL CODE	DA1-35065NB-B55C
EAN	4015081714131
PRODUCT LENGTH/DEPTH	270 mm
PRODUCT HEIGHT	540 mm
PRODUCT WIDTH	235 mm
PRODUCT WEIGHT	22.5 kg

CERTIFICATIONS

Certified by UL for use in Canada
IEC/EN61800-5
RoHS, ISO 9001
UL
CE
CSA-C22.2 No. 14
Specification for general requirements: IEC/EN 61800-2
EAC
UL 508C
DNV
Safety: EN 61800-5-1: 2003

UkrSEPRO
UL Category Control No.: NMMS, NMMS7
RCM
UL report applies to both US and Canada
IEC/EN61800-3
CUL
UL File No.: E172143
IEC/EN 61800-3

CATALOG NOTES

The brake resistors are assigned based on the maximum rated power of the variable frequency drive. Additional brake



Powering Business Worldwide

Apparent power

APPARENT POWER AT 600 V	67.55 kVA
--------------------------------	-----------

Climatic environmental conditions

ALTITUDE	Max. 4000 m Max. 1000 m Above 1000 m with 1 % derating per 100 m
-----------------	---

AMBIENT OPERATING TEMPERATURE - MAX	40 °C
--	-------

AMBIENT STORAGE TEMPERATURE - MAX	60 °C
--	-------

AMBIENT OPERATING TEMPERATURE - MIN	-10 °C
--	--------

AMBIENT OPERATING TEMPERATURE AT 150% OVERLOAD - MAX	40 °C
---	-------

AMBIENT OPERATING TEMPERATURE AT 150% OVERLOAD - MIN	-10 °C
---	--------

AMBIENT STORAGE TEMPERATURE - MIN	-40 °C
--	--------

CLIMATIC PROOFING	< 95 average relative humidity (RH), no condensation, no corrosion
--------------------------	--

resistors and designs (e.g. different duty cycles) are available upon request.

Braking function

BRAKING RESISTANCE	12 Ω
---------------------------	-------------

BRAKING TORQUE	Max. 100 % of rated operational current I_e with external braking resistor - Main circuit Max. 30 % MN, Standard - Main circuit Max. 100 % of rated operational current I_e , variable, DC - Main circuit
-----------------------	---

SWITCH-ON THRESHOLD FOR THE BRAKING TRANSISTOR	975 VDC
---	---------

Control circuit

NUMBER OF INPUTS (ANALOG)	2
----------------------------------	---

NUMBER OF INPUTS (DIGITAL)	5
-----------------------------------	---

NUMBER OF OUTPUTS (ANALOG)	2
-----------------------------------	---

NUMBER OF OUTPUTS (DIGITAL)	2
------------------------------------	---

NUMBER OF RELAY OUTPUTS	2 (parameterizable, 1 N/O and 1 changeover contact, 6 A (250 V, AC-1) / 5 A (30 V, DC-1))
--------------------------------	---

RATED CONTROL VOLTAGE (UC)	24 V DC (external, max. 100 mA)
-----------------------------------	---------------------------------

Design verification

10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION	Does not apply, since the

General information

CABLE LENGTH	150 m, unscreened, maximum permissible, Motor feeder 100 m, screened, maximum permissible, Motor feeder 300 m, unscreened, with motor choke, maximum permissible, Motor feeder 200 m, screened, with motor choke, maximum permissible, Motor feeder
COMMUNICATION INTERFACE	SmartWire-DT, optional EtherCAT, optional CANopen®, built in DeviceNet, optional PROFIBUS, optional Modbus RTU, built in Ethernet IP, optional PROFINET, optional OP-Bus (RS485), built in Modbus-TCP, optional
CONNECTION TO SMARTWIRE-DT	Yes In conjunction with DX-NET-SWD1 SmartWire DT module
DEGREE OF PROTECTION	NEMA 12 IP55
FITTED WITH:	OLED display Additional PCB protection Internal DC link Brake chopper IGBT inverter DC link choke PC connection Breaking resistance Control unit
FRAME SIZE	FS5
FUNCTIONS	4-quadrant operation possible
MOUNTING POSITION	Vertical
PRODUCT CATEGORY	Variable frequency drives
PROTECTION	Finger and back-of-hand proof, Protection against direct contact (BGV A3, VBG4)
PROTOCOL	EtherNet/IP CAN PROFIBUS MODBUS PROFINET IO Other bus systems DeviceNet

AGAINST ELECTRIC SHOCK	entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID	1350 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION DETAILS	Operation (with 150 % overload)
HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID	0 W
RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)	65 A
STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS	0 W

	TCP/IP
SAFETY FUNCTION/LEVEL	STO (Safe Torque Off, SIL2, PLc Cat 2)
SUITABLE FOR	Branch circuits, (UL/CSA)

Main circuit

EFFICIENCY	97 % (η)
HEAT DISSIPATION AT CURRENT/SPEED	1058 W at 100% current and 90% speed 328 W at 25% current and 0% speed 328 W at 25% current and 50% speed 328 W at 50% current and 0% speed 370 W at 50% current and 50% speed 420 W at 50% current and 90% speed 649 W at 100% current and 0% speed 836 W at 100% current and 50% speed
INPUT CURRENT ILN AT 150% OVERLOAD	70.4 A
LEAKAGE CURRENT AT GROUND IPE - MAX	65 mA
MAINS SWITCH-ON FREQUENCY	Maximum of one time every 30 seconds
MAINS VOLTAGE - MAX	600 V
MAINS VOLTAGE - MIN	500 V
OPERATING MODE	Optional: Vector control with feedback (CLV) U/f control Speed control with slip compensation Sensorless vector control (SLV)
OUTPUT FREQUENCY - MAX	500 Hz
OUTPUT FREQUENCY - MIN	0 Hz
OUTPUT VOLTAGE (U2)	500 V AC, 3-phase 600 V AC, 3-phase
OVERLOAD CURRENT IL AT 150% OVERLOAD	97.5 A
RATED CONTROL SUPPLY VOLTAGE	10 V DC (Us, max. 10 mA)
RATED FREQUENCY - MAX	62 Hz
RATED FREQUENCY - MIN	48 Hz
RATED OPERATIONAL CURRENT (IE) AT 150% OVERLOAD	65 A
RATED OPERATIONAL POWER AT 500 V, 50 HZ, 3-PHASE	45 kW

Motor rating

ASSIGNED MOTOR CURRENT IM AT 500 V, 50 HZ, 150% OVERLOAD	65 A
ASSIGNED MOTOR CURRENT IM AT 525 V, 50 HZ, 150% OVERLOAD	62 A
ASSIGNED MOTOR CURRENT IM AT 550 - 600 V, 60 HZ, 150% OVERLOAD	62 A
ASSIGNED MOTOR POWER AT 575/600 V, 60 HZ, 3-PHASE	60 HP

RATED OPERATIONAL POWER AT 525 V, 50 HZ, 3-PHASE	45 kW
RATED OPERATIONAL VOLTAGE	500 V AC, 3-phase 600 V AC, 3-phase
RESOLUTION	0.1 Hz (Frequency resolution, setpoint value)
SHORT-CIRCUIT PROTECTION	LPJ fuse used together with JM60100-3 fuse base, Power wiring, Assigned switching and protective elements NH fuse used together with TB00-D fuse base, Power wiring, Assigned switching and protective elements
SHORT-CIRCUIT PROTECTION RATING	100 A, UL (Class CC or J), Safety device (fuse or miniature circuit-breaker), Power Wiring
STARTING CURRENT - MAX	200 %, IH, max. starting current (High Overload), for 4 seconds every 40 seconds, Power section
SUPPLY FREQUENCY	50/60 Hz
SWITCHING FREQUENCY	8 kHz, 4 - 24 kHz adjustable (audible), fPWM, Power section, Main circuit
SYSTEM CONFIGURATION TYPE	AC supply systems with earthed center point
VOLTAGE RATING - MAX	600 VAC

Resources

[eaton-powerxl-dx-com-stick-3-ap040190-en-us.pdf](#)

[eaton-powerxl-da1-operating-pm-bldc-motors-ap040051-en-us.pdf](#)

[eaton-powerxl-da1-master-slave-operation-ap040026-en-us.pdf](#)

[Electromagnetic compatibility \(EMC\)](#)

[eaton-powerxl-da1-vector-control-induction-motors-ap040028-en-us.pdf](#)

[eaton-powerxl-da1-motor-vf-curves-induction-motors-ap040018-en-us.pdf](#)

[eaton-powerxl-da1-derating-ap040039-en-us.pdf](#)

APPLICATION NOTES

[eaton-powerxl-vfd-dual-rating-ap040114-en-us.pdf](#)

[eaton-powerxl-da1-hoist-applications-ap040032-en-us.pdf](#)

[eaton-powerxl-da1-starting-stopping-operation-ap040030-en-us.pdf](#)

[eaton-powerxl-da1-dc1-de1-internal-motor-protection-ap040016-en-us.pdf](#)

[eaton-powerxl-da1-pointer-to-parameter-ap040133-en-us.pdf](#)

[eaton-powerxl-da1-pid-controller-ap040025-en-us.pdf](#)

[eaton-powerxl-da1-droop-function-ap040023-en-us.pdf](#)

[Start, Stopp und Betrieb](#)

	eaton-powerxl-da1-dc1-de1-conformal-coating-ap040182-en-us.pdf eaton-powerxl-da1-i-o-configuration-ap040034-en-us.pdf eaton-powerxl-da1-dc1-db1-de1-rapidlink5-firmware-update-ap040214-en-us.pdf eaton-powerxl-da1-dc1-de1-system-bus-ap040022-en-us.pdf eaton-powerxl-da1-use-of-multiple-ramps-ap040031-en-us.pdf eaton-powerxl-da1-set-point-setting-ap040040-en-us.pdf
BROCHURES	eaton-powerxl-variable-frequency-drives-dc1-da1-brochure-br040001en-en-us.pdf
CATALOGUES	eaton-drives-soft-starter-catalog-ca04020001zen-us.pdf
DECLARATIONS OF CONFORMITY	eaton-variable-frequency-drive-declaration-of-conformity-eu250662en.pdf eaton-variable-frequency-drive-declaration-of-conformity-uk251145en.pdf
DRAWINGS	eaton-frequency-inverter-dimensions-024.eps eaton-frequency-inverter-3d-drawing-015.eps
ECAD MODEL	DA-CE-ETN.DA1-35065NB-B55C
INSTALLATION INSTRUCTIONS	eaton-da1-variable-frequency-drive-il04020011z.pdf
INSTALLATION VIDEOS	PowerXL Variable Frequency Drives DC1 and DA1 - EN Video PowerXL DA1
MANUALS AND USER GUIDES	eaton-powerxl-vfd-profinet-manual-mn040062en-us.pdf

	eaton-da1-variable-frequency-drive-mn040063-en-us.pdf eaton-powerxl-da1-application-manual-mn04020006z-en-us.pdf MN040018_EN eaton-canopen-communication-manual-for-variable-frequency-drives-variable-speed-starters-da1-db1-dc1-de11-mn040019-en-us.pdf eaton-powerxl-da1-installation-manual-mn04020005z-en-us.pdf
MCAD MODEL	eaton-general-purpose-drives-mcad-drawings-da1-fs5-ip55.dwg DA-CS-da1_fs5_ip55
MULTIMEDIA	Looking for variable frequency drives DC1 and DA1 which can be used in harsh environments? System solutions based on EtherCAT
PRODUCT NOTIFICATIONS	eaton-drives-ecodesign-directive-mz040046en-en.pdf
SOFTWARE, FIRMWARE, AND APPLICATIONS	eaton-powerxl-da1-canopen-eds-v250.zip eaton-powerxl-da1-swd-codesys-v3-library.zip eaton-powerxl-dx-cbl-pc-3m0-usb-driver.zip eaton-powerxl-da1-profibus-gsd-v216.zip eaton-powerxl-da1-profinet-tia-v12-library.zip eaton-powerxl-dx-comstick3-ble-drivers.zip eaton-powerxl-da1-profinet-gsdml-v226.zip eaton-powerxl-dx-cbl-pc-1m5-usb-driver.zip

[eaton-powerxl-da1-
canopen-codesys-v3-
library.zip](#)

[eaton-powerxl-da1-
ethercat-esi-v310.zip](#)

[eaton-powerxl-da1-
ethercat-esi-for-omron-
v311.zip](#)

[eaton-powerxl-da1-
devicenet-eds-v100.zip](#)

[eaton-powerxl-da1-
ethernetip-eds-v150.zip](#)

[eaton-powerxl-da1-
firmware-release-note-
mz040041en-us.pdf](#)

[eaton-powerxl-
pcsoftware-drivesconnect-
v1501.zip](#)

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



Eaton Corporation plc Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2026 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

