

Specifications



Photo is representative



Eaton 192400

Eaton Moeller® series EMS2 Reversing starter, 24 V DC, 1,5 - 7 (AC-53a), 9 (AC-51) A, Screw terminals, Controlled stop, PTB 19 ATEX 3000 EMS2-ROSF-Z-9-24VDC

General specifications

PRODUCT NAME	Eaton Moeller® series EMS2 Reversing starter
---------------------	--

CATALOG NUMBER	192400
-----------------------	--------

MODEL CODE	EMS2-ROSF-Z-9-24VDC
-------------------	---------------------

EAN	4015081930975
------------	---------------

PRODUCT LENGTH/DEPTH	114.5 mm
-----------------------------	----------

PRODUCT HEIGHT	160 mm
-----------------------	--------

PRODUCT WIDTH	22.5 mm
----------------------	---------

PRODUCT WEIGHT	0.35 kg
-----------------------	---------

CERTIFICATIONS	IEC 61508 IEC/EN 60947-4-2 EN ISO 13849 UL508 UL File No.: E29096 UL Category Control No.: NLDX, NLDX7 PTB 19 ATEX 3000 UL 60947-4-1 CSA-C22.2 No. 60947-4-1-14 CE marking UL listed Certified by UL for use in Canada UL report applies to both US and Canada
-----------------------	--

Climatic environmental conditions

AMBIENT OPERATING TEMPERATURE - MAX	70 °C
--	-------

AMBIENT STORAGE TEMPERATURE - MAX	80 °C
--	-------

AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
--	--------

AMBIENT STORAGE TEMPERATURE - MIN	40 °C
--	-------

Contacts

NUMBER OF AUXILIARY CONTACTS (NORMALLY CLOSED CONTACTS)	1
--	---

NUMBER OF AUXILIARY CONTACTS (NORMALLY OPEN CONTACTS)	1
--	---

NUMBER OF CONTACTS (CHANGE-OVER CONTACTS)	1
--	---

Design verification

10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION	Does not apply, since the

Electrical rating

RATED ACTUATING CURRENT (IC)	5 mA
RATED CONTROL SUPPLY CURRENT IS	40 mA
RATED CONTROL SUPPLY VOLTAGE	19.2 - 30 V DC
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	24 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	24 V
RATED CONTROL VOLTAGE (UC)	24 V (Actuating circuit ON, L, R)
RATED OPERATIONAL CURRENT (IE)	9 A
RATED OPERATIONAL CURRENT (IE) AT AC-15, 220 V, 230 V, 240 V	2 A
RATED OPERATIONAL CURRENT (IE) AT AC-3, 380 V, 400 V, 415 V	7 A
RATED OPERATIONAL CURRENT (IE) AT AC-51	9 A
RATED OPERATIONAL CURRENT (IE) AT AC-53A - MAX	7 A
RATED OPERATIONAL CURRENT (IE) AT DC-13, 24 V	2 A
RATED OPERATIONAL POWER AT AC-3, 220/230 V, 50 HZ	1.5 kW
RATED OPERATIONAL POWER AT AC-3, 380/400 V, 50 HZ	3 kW
RATED OPERATIONAL POWER AT AC-53A, 380/400 V, 50 HZ	3 kW
RATED OPERATIONAL VOLTAGE	42 - 550 V 500 V AC
SWITCHING LEVEL	-3 - 9.6 V DC, Switching level "Low", Actuating circuit (ON, L, R) < 5 V DC, Switching level "confirm Off", Actuating circuit (ON, L, R) 19.2 - 30 V DC, Switching level "High", Actuating circuit (ON, L, R)

AGAINST ELECTRIC SHOCK	entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID	13 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION DETAILS	If necessary, Allow for derating
HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID	0 W
RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)	9 A
STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS	2 W

Electro magnetic compatibility

RADIO INTERFERENCE CLASS	EN 55011 Class A (EN 61000-6-3, emitted interference, radiated)
---------------------------------	--

Features & functions

FITTED WITH:	fuse
FUNCTIONS	Motor protection Controlled stop DOL starting Reversing start Temperature compensated overload protection

General information

CLASS	CLASS 10 A
CONNECTION TO SMARTWIRE-DT	No
DEGREE OF PROTECTION	IP20 NEMA Other
MODEL	Reversing starter
MOUNTING METHOD	Mounting on Busbar 30 mm Rail mounting possible Motor starter Feeder System Mounting on Busbar 60 mm Top-hat rail fixing (according to IEC/EN 60715, 35 mm)
MOUNTING POSITION	Motor feeder at bottom Vertical
OVERLOAD RELEASE CURRENT SETTING - MAX	9 A
OVERLOAD RELEASE CURRENT SETTING - MIN	1.5 A
PRODUCT CATEGORY	Electronic motor starter
RESIDUAL RIPPLE	≤ 5 % (input voltage)
TERMINAL CAPACITY	0.14 - 2.5 mm ² , Control circuit cables 0.2 - 2.5 mm ² , Main cables
TERMINAL CAPACITY (AWG)	26 - 14, Control circuit cables 24 - 14, Main cables
TYPE	Reversing starter (complete device)
VOLTAGE TYPE	DC

Safety

EXPLOSION SAFETY CATEGORY FOR DUST	ATEX dust-ex-protection, II (2) G [Ex e] [Ex d] [Ex px] ATEX dust-ex-protection, II (2) D [Ex t] [Ex p]
SAFETY PARAMETER (EN ISO 13849-1)	3 (safe switch off), Category PL e, Performance level (safe switch off) 60 (safe switch off) / 70 (motor protection) years; MTTFD
SAFETY PARAMETER (IEC 62061)	99 % (safe switch off) / 98 % (motor protection), DC PFHd [FIT]: 2.3 (Safe switch off) Λsu [FIT]: 1072 (Safe switch off) / 969 (Motor protection) Λdd [FIT]: 580 (Safe switch off) / 601 (Motor protection) Λdu [FIT]: 2.3 (Safe switch off) / 11 (Motor protection)
	99 %, SFF SIL 3 (Safe switch off) / SIL 2 (Motor protection) Opening delay [ms]: 200 (safe switch off) / Class 10A (motor protection) Λsd [FIT]: 0

Resources

APPLICATION NOTES	eaton-motor-starter-ems2-setting-motor-protection-twincat3-ap034001-en-us.pdf
BROCHURES	eaton-ems2-electronic-motorstarter-brochure-br034001en-en-us.pdf
CHARACTERISTIC CURVE	eaton-contactors-ems2-reversing-starter-characteristic-curve-002.eps
	eaton-contactors-ems2-reversing-starter-characteristic-curve-006.eps
	eaton-contactors-ems2-reversing-starter-characteristic-curve-005.eps
	eaton-contactors-ems2-reversing-starter-characteristic-curve-007.eps
	eaton-contactors-ems2-reversing-starter-characteristic-curve-004.eps
DECLARATIONS OF CONFORMITY	eaton-reversing-starter-declaration-of-conformity-uk251116en.pdf eaton-reversing-starter-declaration-of-conformity-eu250633en.pdf
DRAWINGS	eaton-contactors-ems2-reversing-starter-dimensions-004.eps eaton-contactors-ems2-reversing-starter-3d-drawing-004.eps
ECAD MODEL	DA-CE-ETN.EMS2-ROSF-Z-9-24VDC
INSTALLATION INSTRUCTIONS	IL034089ZU
INSTALLATION VIDEOS	Eaton's electronic motor starter EMS2

MANUALS AND USER GUIDES	eaton-electronic-motor-starter-ems2-manual-mn034003en-us.pdf
MCAD MODEL	eaton-motor-starter-mcad-drawings-ems2-rosf-z-24vdc.dwg DA-CS-ems2_rosf_z_24vdc
SALES NOTES	eaton-ems2-electronic-motorstarter-flyer-fl034007en-en-us.pdf

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
DATE:



Eaton Corporation plc Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2026 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

