

Specifications



Eaton 259539

Eaton Moeller series NZM Undervoltage release, 208-240VAC, +2early N/O, for NZM1

General specifications

PRODUCT NAME	Eaton Moeller series NZM Undervoltage release
CATALOG NUMBER	259539
MODEL CODE	NZM1-XUHIV208-240AC
EAN	4015082595395
PRODUCT LENGTH/DEPTH	37 mm
PRODUCT HEIGHT	66 mm
PRODUCT WIDTH	32 mm
PRODUCT WEIGHT	0.084 kg
COMPLIANCES	IEC UL/CSA RoHS conform
CERTIFICATIONS	CSA (File No. 22086) CSA certified CE marking IEC60947 CSA (Class No. 1437-01) UL489 UL (File No. E140305) CSA-C22.2 No. 5-09 UL (Category Control Number DIHS) UL listed

Delivery programme

FITTED WITH: Two early-make auxiliary contacts

FRAME NZM1

SPECIAL FEATURES

- Undervoltage release with 2 early-make auxiliary contacts, e.g., for early-make connection of undervoltage release in main switch applications, as well as for interlock and load shedding circuits.
- For use with emergency-stop devices in connection with an emergency-stop button.
- When the under-voltage trip is switched off, accidental contact with the circuit breaker's primary contacts is prevented when switched on.
- Early make of auxiliary contacts on switching on and off (manual operation): approx. 20 ms
- Undervoltage releases cannot be installed simultaneously with NZM...-XHIV... early-make auxiliary contact or NZM...-XA... shunt release.

SUITABLE FOR Off-load switch

TYPE

- Accessory
- Undervoltage release with early-make auxiliary contact

USED WITH NZM1(-4), N(S)1(-4)

Design verification to IEC/EN 61439

10.10 TEMPERATURE RISE

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 SHORT-CIRCUIT RATING

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.12 ELECTROMAGNETIC COMPATIBILITY

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 MECHANICAL FUNCTION

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

10.2.2 CORROSION RESISTANCE

Meets the product standard's requirements.

10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES

Meets the product standard's requirements.

10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT

Meets the product standard's requirements.

10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS

Meets the product standard's requirements.

10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION

Meets the product standard's requirements.

10.2.5 LIFTING

Does not apply, since the entire switchgear needs to be evaluated.

10.2.6 MECHANICAL IMPACT

Does not apply, since the entire switchgear needs to be evaluated.

10.2.7 INSCRIPTIONS

Meets the product standard's requirements.

10.3 DEGREE OF PROTECTION OF ASSEMBLIES

Does not apply, since the entire switchgear needs to be evaluated.

10.4 CLEARANCES AND CREEPAGE DISTANCES

Meets the product standard's requirements.

10.5 PROTECTION

Does not apply, since the

AGAINST ELECTRIC SHOCK	entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.

Technical data - electrical

**DROP-OUT VOLTAGE OF
UNDervOLTAGE RELEASE** 0.7 x Us
AC/DC - MAX

**DROP-OUT VOLTAGE OF
UNDervOLTAGE RELEASE** 0.35 x Us
AC/DC - MIN

**ELECTRIC CONNECTION
TYPE** Screw connection

**MINIMUM COMMAND
TIME - MAX** 15 ms

**MINIMUM COMMAND
TIME - MIN** 10 ms

**PICK-UP POWER
CONSUMPTION AT AC
(UNDervOLTAGE
RELEASE)** 1.5 VA

**PICK-UP POWER
CONSUMPTION AT DC
(UNDervOLTAGE
RELEASE)** 0.8 W

POWER CONSUMPTION 1.5 VA (AC)
0.8 W (DC)

**RATED CONTROL SUPPLY
VOLTAGE** 208 - 240 V 50/60 Hz

**RATED CONTROL SUPPLY
VOLTAGE (US) AT AC, 50
HZ - MAX** 240 V

**RATED CONTROL SUPPLY
VOLTAGE (US) AT AC, 50
HZ - MIN** 208 V

**RATED CONTROL SUPPLY
VOLTAGE (US) AT AC, 60
HZ - MAX** 240 V

**RATED CONTROL SUPPLY
VOLTAGE (US) AT AC, 60
HZ - MIN** 208 V

**RATED CONTROL
VOLTAGE (RELAY
CONTACTS)** 208 V AC
240 V AC

REACTION TIME 19 ms

**VOLTAGE TOLERANCE -
MAX** 1.1

**VOLTAGE TOLERANCE -
MIN** 0.85

VOLTAGE TYPE AC

Technical data - mechanical

CONNECTION TYPE With terminal block on the
left-hand switch side

**NUMBER OF CONTACTS
(CHANGE-OVER
CONTACTS)** 0

**NUMBER OF CONTACTS
(NORMALLY CLOSED
CONTACTS)** 0

**NUMBER OF CONTACTS
(NORMALLY OPEN
CONTACTS)** 2

SPECIAL FEATURES

- Undervoltage release with 2 early-make auxiliary contacts, e.g., for early-make connection of undervoltage release in main switch applications, as well as for interlock and load shedding circuits.
- For use with emergency-stop devices in connection with an emergency-stop button.
- When the under-voltage trip is switched off, accidental contact with the circuit breaker's primary contacts is prevented when switched on.
- Early make of auxiliary contacts on switching on and off (manual operation): approx. 20 ms
- Undervoltage releases cannot be installed simultaneously with NZM...-XHIV... early-make auxiliary contact or NZM...-XA... shunt release.

Technical data - mechanical - terminals

TERMINAL CAPACITY (SOLID/FLEXIBLE CONDUCTOR)

0.75 mm² - 2.5 mm² (1x)
for undervoltage releases,
off-delayed with ferrule
18 - 14 AWG (2x) for
undervoltage releases, off-
delayed
0.75 mm² - 2.5 mm² (2x)
for undervoltage releases,
off-delayed with ferrule
0.75 mm² - 2.5 mm² (2x) at
shunt release with ferrule
18 - 14 AWG (2x) at shunt
release
0.75 mm² - 2.5 mm² (1x) at
shunt release with ferrule
18 - 14 AWG (1x) for
undervoltage releases, off-
delayed
18 - 14 AWG (1x) at shunt
release

Resources

BROCHURES

[eaton-digital-nzm-
brochure-br013003en-en-
us.pdf](#)

[eaton-feerum-the-whole-
grain-solution-success-
story-en-us.pdf](#)

CATALOGUES

[eaton-digital-nzm-catalog-
ca013003en-en-us.pdf](#)

DRAWINGS

[eaton-circuit-breaker-
release-nzm-mccb-
dimensions.eps](#)

[eaton-circuit-breaker-
undervoltage-nzm-mccb-
3d-drawing-004.eps](#)

ECAD MODEL

[ETN.259539.edz](#)

INSTALLATION INSTRUCTIONS

[eaton-circuit-breaker-
nzm1-xa-xahiv-xhiv-xu-
xuhiv-il01203002z.pdf](#)

INSTALLATION VIDEOS

[Introduction of the new
digital circuit breaker NZM](#)

[The new digital NZM
Range](#)

[eaton-int-tripping-acc-
mcad-drawings-nzm1-
xhiv.dwg](#)

MCAD MODEL

[eaton-accessories-mcad-
drawings-nzm1-xu.dwg](#)

[eaton-int-tripping-acc-
mcad-3d-models-nzm1-
xhiv.stp](#)

TECHNICAL DATA SHEETS

[eaton-nzm-technical-
information-sheet](#)

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



Eaton Corporation plc Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2026 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

