

RCD / RCBO Cross-Reference — Siemens 5SM/5SV, Schneider iLD/iC60 RCBO, ABB F200/DS200, Eaton PFIM/FRCDM, Hager by Poles, Rating, Sensitivity and Type

cBallast Technical Sourcing · generated 2026-09-29 · cballast.com/documents/rcd-rcbo-cross-reference-siemens-schneider-abb-eaton-hager-by-poles-rating-sensitivity-type · first 275 rows; the full table is online

Residual current devices are matched by number of poles, rated current In, rated residual operating current I9Fà (30 mA personal protection, 100/300 mA fire protection, 300/500 mA selective) and type: AC (sinusoidal residual current only), A (AC and pulsating DC — the minimum for circuits with electronic loads), F (mixed frequencies, single-phase drives) and B (smooth DC, three-phase drives and EV charging). RCBOs combine residual and overcurrent protection in one device and are additionally matched by curve. Type A can replace type AC; type B can replace A and F; the reverse is not permitted.

In · I9Fà	Siemens	Schneider Electric	ABB	Eaton	Hager
RCBO · 1P+N · 6 A · 30 mA	—	A9DC4606, A9DG4606	—	—	—
RCBO · 1P+N · 20 A · 300 mA	—	A9DF8620	—	—	—
RCBO · 1P+N · 63 A · 40 mA	—	A9MEM1563	—	—	—
RCBO · 1P+N · type A · 6 A · 30 mA	—	A9TDFD606, A9TDF3606, A9TDFC606	DS201C6A30	—	—
RCBO · 1P+N · type A · 10 A · 30 mA	—	A9TDFC610, A9TDE3610, A9TDF3610, A9TDEC610, A9TDFD610	DS201C10A30	—	—
RCBO · 1P+N · type A · 13 A · 30 mA	—	—	DS201C13A30	—	—
RCBO · 1P+N · type A · 16 A · 30 mA	—	A9TDF3616, A9TDFD616, A9TDE3616, A9TDFC616, A9TDEC616	DS201C16A30	—	—
RCBO · 1P+N · type A · 20 A · 30 mA	—	A9TDFD620	—	—	—
RCBO · 1P+N · type A · 25 A · 30 mA	—	A9TDFC625, A9TDFD625, A9TDF3625	—	—	—
RCBO · 1P+N · type A · 32 A · 30 mA	—	A9TDFC632, A9D33632, A9TDFD632, A9TDF3632	—	—	—
RCBO · 1P+N · type A · 40 A · 30 mA	—	A9TDFC640, A9TDF3640	—	—	—
RCBO · 1P+N · type A · 50 A · 30 mA	—	—	DS201C50A30	—	—
RCBO · 1P+N · type A · 63 A · 30 mA	—	—	DS201C63A30	—	—
RCBO · 1P+N · type AC · 6 A · 30 mA	—	A9DC3606, A9DG3606, A9D56606, A9D32606, A9DF3606, A9D33606	—	—	—
RCBO · 1P+N · type AC · 6 A · 300 mA	—	A9DF7606, A9D42606	—	—	—
RCBO · 1P+N · type AC · 10 A · 30 mA	—	A9DF3610, A9DG3610, A9DC3610, A9DC4610, A9D33610, A9D32610	—	—	—
RCBO · 1P+N · type AC · 10 A · 300 mA	—	A9DC7610, A9DF7610, A9D42610	—	—	—
RCBO · 1P+N · type AC · 13 A · 30 mA	—	A9D56613, A9D33613, A9D32613	—	—	—
RCBO · 1P+N · type AC · 16 A · 30 mA	—	A9DC3616, A9DC4616, A9D56616, A9DF3616, A9D32616, A9DG3616	—	—	—
RCBO · 1P+N · type AC · 16 A · 300 mA	—	A9DC7616, A9DF7616	—	—	—
RCBO · 1P+N · type AC · 20 A · 30 mA	—	A9DF3620, A9DC3620, A9DC4620, A9DG4620	—	—	—
RCBO · 1P+N · type AC · 20 A · 300 mA	—	A9D42620, A9DF7620	—	—	—
RCBO · 1P+N · type AC · 25 A · 30 mA	—	A9D33625, A9DF3625, A9D32625, A9DC4625, A9DC3625, A9DG4625	—	—	—
RCBO · 1P+N · type AC · 25 A · 300 mA	—	A9DF7625	—	—	—

RCBO · 1P+N · type AC · 32 A · 30 mA	—	A9DF3632, A9DC4632, A9DG4632, A9DC3632	—	—	—
RCBO · 1P+N · type AC · 32 A · 300 mA	—	A9D42632, A9DF7632	—	—	—
RCBO · 1P+N · type AC · 40 A · 30 mA	—	A9DF3640, A9DC3640	—	—	—
RCBO · 1P+N · type AC · 40 A · 300 mA	—	A9DF7640	—	—	—
RCBO · 2P · 30 A · 30 mA	—	A9D27225	—	—	—
RCBO · 2P · type A · 6 A · 30 mA	5SU1324-6FP06, 5SU1324-7FP06, 5SU1324-7FR06, 5SU1324-6FA06	—	—	—	—
RCBO · 2P · type A · 10 A · 30 mA	5SU1324-7FP10, 5SU1324-6FP10, 5SU1324-7FR10	A9DC4210, A9TDF4210	—	—	—
RCBO · 2P · type A · 13 A · 30 mA	5SU1324-7FP13, 5SU1324-6FP13	—	—	—	—
RCBO · 2P · type A · 15 A · 30 mA	5SU1324-7FN15, 5SU1324-6FN15	A9D14215, A9D34215, A9DC4215, A9TDF4215, A9TDE4215	—	PKPM2-15/2/C/003A-OL	—
RCBO · 2P · type A · 16 A · 30 mA	5SU1324-7FP16, 5SU1324-6FP16, 5SU1324-7FR16, 5SU1324-7FM16, 5SU1324-6FR16	A9TDF4216, A9TDE4216	—	—	—
RCBO · 2P · type A · 20 A · 30 mA	5SU1324-7FP20, 5SU1324-7FN20, 5SU1324-6FN20, 5SU1324-6FR20, 5SU1324-6FP20, 5SU1324-7FR20	A9DC4220, A9TDF4220, A9TDE4220	—	PKPM2-20/2/C/003A-OL	—
RCBO · 2P · type A · 25 A · 30 mA	5SU1324-7FP25, 5SU1324-6FP25, 5SU1324-7FR25	A9DC4225, A9TDF4225, A9TDE4225	—	—	—
RCBO · 2P · type A · 32 A · 30 mA	5SU1324-7FR32, 5SU1324-7FP32, 5SU1324-6FP32	A9DC4232	—	—	—
RCBO · 2P · type AC · 6 A · 30 mA	—	—	—	111638	—
RCBO · 2P · type AC · 10 A · 30 mA	—	A9D17210, A9D37210, A9D27210, A9D47210	—	PKPM2-10/2/C/003-A, PKPM2-10/2/B/003-A	—
RCBO · 2P · type AC · 10 A · 100 mA	—	—	—	PKPM2-10/2/C/01-A, PKPM2-10/2/B/01-A	—
RCBO · 2P · type AC · 10 A · 300 mA	—	A9D54210	—	—	—
RCBO · 2P · type AC · 13 A · 30 mA	—	A9D17213, A9D37213, A9D47213, A9D27213	—	PKPM2-13/2/C/003-A, PKPM2-13/2/B/003-A	—
RCBO · 2P · type AC · 13 A · 100 mA	—	—	—	PKPM2-13/2/B/01-A	—
RCBO · 2P · type AC · 16 A · 30 mA	—	A9D17216, A9D37216, A9D27216, A9D47216	—	PKPM2-16/2/B/003-A	—
RCBO · 2P · type AC · 16 A · 100 mA	—	—	—	PKPM2-16/2/C/01-A, PKPM2-16/2/B/01-A, 193781	—
RCBO · 2P · type AC · 16 A · 300 mA	—	A9D54216	—	—	—
RCBO · 2P · type AC · 20 A · 30 mA	—	A9D17220, A9D37220, A9D27220	—	—	—
RCBO · 2P · type AC · 20 A · 100 mA	—	—	—	PKPM2-20/2/C/01-A, PKPM2-20/2/B/01-A	—
RCBO · 2P · type AC · 20 A · 300 mA	—	A9D54220	—	—	—
RCBO · 2P · type AC · 25 A · 30 mA	—	A9D17225, A9D37225, A9D47225	—	PKP62-25/2/C/003-A, PKP62-25/2/B/003-A	—
RCBO · 2P · type AC · 25 A · 100 mA	—	—	—	PKP62-25/2/C/01-A, PKP62-25/2/B/01-A	—
RCBO · 2P · type AC · 25 A · 300 mA	—	A9D54225	—	—	—

RCBO · 2P · type AC · 32 A · 30 mA	—	A9D17232, A9D37232, A9D27232, A9D47232	—	PKP62-32/2/B/003-A	—
RCBO · 2P · type AC · 32 A · 100 mA	—	—	—	PKP62-32/2/C/01-A, 193828, PKP62-32/2/B/01-A	—
RCBO · 2P · type AC · 32 A · 300 mA	—	A9D54232	—	—	—
RCBO · 2P · type AC · 40 A · 30 mA	—	—	—	PKP62-40/2/C/003-A, PKP62-40/2/B/003-A	—
RCBO · 2P · type AC · 40 A · 100 mA	—	—	—	PKP62-40/2/C/01-A	—
RCBO · 3P · type A · 6 A · 30 mA	5SU1336-6FP06, 5SU1336-7FP06	—	—	—	—
RCBO · 3P · type A · 6 A · 300 mA	5SU1636-6FP06, 5SU1636-7FP06	—	—	—	—
RCBO · 3P · type A · 10 A · 30 mA	5SU1336-7FP10, 5SU1336-6FP10	—	—	—	—
RCBO · 3P · type A · 10 A · 300 mA	5SU1636-6FP10, 5SU1636-7FP10	—	—	—	—
RCBO · 3P · type A · 13 A · 30 mA	5SU1336-6FP13	—	—	—	—
RCBO · 3P · type A · 16 A · 30 mA	5SU1336-7FP16, 5SU1336-6FP16	—	—	—	—
RCBO · 3P · type A · 16 A · 300 mA	5SU1636-6FP16	—	—	—	—
RCBO · 3P · type A · 20 A · 30 mA	5SU1336-6FP20, 5SU1336-7FP20	—	—	—	—
RCBO · 3P · type A · 20 A · 300 mA	5SU1636-6FP20	—	—	—	—
RCBO · 3P · type A · 25 A · 30 mA	5SU1336-7FP25, 5SU1336-6FP25	—	—	—	—
RCBO · 3P · type A · 25 A · 300 mA	5SU1636-7FP25, 5SU1636-6FP25	—	—	—	—
RCBO · 3P · type A · 32 A · 30 mA	5SU1336-7FP32	—	—	—	—
RCBO · 3P · type A · 32 A · 300 mA	5SU1636-6FP32, 5SU1636-7FP32	—	—	—	—
RCBO · 3P · type AC · 10 A · 30 mA	—	A9D17310, A9D67310	—	PKPM3-10/3/C/003-A, PKPM3-10/3/B/003-A, PKPM3-10/3/C/003-Li/A, PKPM3-10/3/B/003-Li/A	—
RCBO · 3P · type AC · 10 A · 100 mA	—	—	—	PKPM3-10/3/C/01-A, PKPM3-10/3/C/01-Li/A	—
RCBO · 3P · type AC · 13 A · 30 mA	—	—	—	PKPM3-13/3/C/003-A, PKPM3-13/3/C/003-Li/A, PKPM3-13/3/B/003-A	—
RCBO · 3P · type AC · 13 A · 100 mA	—	—	—	PKPM3-13/3/C/01-A	—
RCBO · 3P · type AC · 16 A · 30 mA	—	A9D17316, A9D67316	—	PKPM3-16/3/C/003-A, PKPM3-16/3/C/003-Li/A, PKPM3-16/3/B/003-A, PKPM3-16/3/B/003-Li/A	—
RCBO · 3P · type AC · 16 A · 100 mA	—	—	—	PKPM3-16/3/C/01-A, PKPM3-16/3/B/01-A, PKPM3-16/3/C/01-Li/A, PKPM3-16/3/B/01-Li/A	—
RCBO · 3P · type AC · 20 A · 30 mA	—	A9D17320	—	PKPM3-20/3/C/003-A, PKPM3-20/3/C/003-Li/A, PKPM3-20/3/B/003-A, PKPM3-20/3/B/003-Li/A	—
RCBO · 3P · type AC · 20 A · 100 mA	—	—	—	PKPM3-20/3/C/01-A, PKPM3-20/3/B/01-A, PKPM3-20/3/C/01-Li/A	—
RCBO · 3P · type AC · 25 A · 30 mA	—	A9D17325, A9D67325	—	PKPM3-25/3/C/003-A, PKPM3-25/3/C/003-Li/A, 193830	—
RCBO · 3P · type AC · 25 A · 100 mA	—	—	—	PKPM3-25/3/C/01-Li/A, 193832	—
RCBO · 3P · type AC · 32 A · 30 mA	—	A9D17332, A9D67332	—	PKPM3-32/3/C/003-A, PKPM3-32/3/C/003-Li/A, 193831	—
RCBO · 3P · type AC · 32 A · 100 mA	—	—	—	PKPM3-32/3/C/01-Li/A, 193833	—

RCBO · 3P+N · 13 A · 30 mA	—	A9DF3713	—	—	—
RCBO · 3P+N · 16 A · 20 mA	—	R9D55716	—	—	—
RCBO · 3P+N · type AC · 10 A · 30 mA	—	A9DF3710, A9DG3710, A9DC3710	—	—	—
RCBO · 3P+N · type AC · 10 A · 300 mA	—	A9DC7710	—	—	—
RCBO · 3P+N · type AC · 16 A · 30 mA	—	A9DC3716, A9DF3716, A9DG3716	—	193845	—
RCBO · 3P+N · type AC · 16 A · 300 mA	—	A9DC7716	—	—	—
RCBO · 3P+N · type AC · 20 A · 30 mA	—	A9DF3720, A9DC3720	—	—	—
RCBO · 3P+N · type AC · 25 A · 30 mA	—	A9DF3725, A9DC3725	—	—	—
RCBO · 3P+N · type AC · 32 A · 30 mA	—	A9DC3732, A9DF3732	—	—	—
RCBO · 3P+N · type AC · 40 A · 30 mA	—	A9DC3740, A9DF3740	—	—	—
RCBO · 4P · type A · 6 A · 30 mA	5SU1346-6FP06, 5SU1346-7FP06	—	—	—	—
RCBO · 4P · type A · 6 A · 300 mA	5SU1646-6FP06, 5SU1646-7FP06	—	—	—	—
RCBO · 4P · type A · 10 A · 30 mA	5SU1346-7FP10, 5SU1346-6FP10	—	—	—	—
RCBO · 4P · type A · 10 A · 300 mA	5SU1646-7FP10	—	—	—	—
RCBO · 4P · type A · 13 A · 30 mA	5SU1346-7FP13, 5SU1346-6FP13	—	—	—	—
RCBO · 4P · type A · 16 A · 30 mA	5SU13467FP16, 5SU1346-6FP16	—	—	—	—
RCBO · 4P · type A · 16 A · 300 mA	5SU1646-7FP16	—	—	—	—
RCBO · 4P · type A · 20 A · 30 mA	5SU1346-6FP20, 5SU1346-7FP20	—	—	—	—
RCBO · 4P · type A · 20 A · 300 mA	5SU1646-6FP20, 5SU1646-7FP20	—	—	—	—
RCBO · 4P · type A · 25 A · 30 mA	5SU1346-7FP25, 5SU1346-6FP25	—	—	—	—
RCBO · 4P · type A · 25 A · 300 mA	5SU1646-7FP25, 5SU1646-6FP25	—	—	—	—
RCBO · 4P · type A · 32 A · 30 mA	5SU1346-7FP32, 5SU1346-6FP32	—	—	—	—
RCBO · 4P · type A · 32 A · 300 mA	5SU1646-6FP32, 5SU1646-7FP32	—	—	—	—
RCBO · 4P · type AC · 10 A · 30 mA	—	A9D67410, A9D77410, A9D87410	—	—	—
RCBO · 4P · type AC · 10 A · 300 mA	—	A9D52410	—	—	—
RCBO · 4P · type AC · 13 A · 30 mA	—	A9D67413, A9D87413, A9D77413, A9D97413	—	—	—
RCBO · 4P · type AC · 16 A · 30 mA	—	A9D67416, A9D77416, A9D87416, A9D97416	—	—	—
RCBO · 4P · type AC · 16 A · 300 mA	—	A9D52416	—	—	—
RCBO · 4P · type AC · 20 A · 30 mA	—	A9D67420, A9D77420, A9D87420	—	—	—
RCBO · 4P · type AC · 20 A · 300 mA	—	A9D52420	—	—	—
RCBO · 4P · type AC · 25 A · 30 mA	—	A9D67425, A9D77425, A9D87425	—	—	—
RCBO · 4P · type AC · 25 A · 300 mA	—	A9D52425	—	—	—
RCBO · 4P · type AC · 32 A · 30 mA	—	A9D67432, A9D77432, A9D87432, A9D97432	—	—	—
RCBO · 4P · type AC · 32 A · 300 mA	—	A9D52432	—	—	—
RCCB · 1P+N · 32 A · 30 mA	—	EVB3S07N4A, EVB3S07NCA	—	—	—
RCCB · 1P+N · type AC · 25 A · 30 mA	—	A9Y80625, A9Y84625	—	—	—
RCCB · 1P+N · type AC · 25 A · 300 mA	—	A9Y85625, A9Y81625	—	—	—
RCCB · 1P+N · type AC · 40 A · 30 mA	—	A9Y84640, A9Y80640	—	—	—

RCCB · 1P+N · type AC · 40 A · 300 mA	—	A9Y85640, A9Y81640	—	—	—
RCCB · 2P · 16 A · 10 mA	5SM2121-6	—	—	—	—
RCCB · 2P · 16 A · 30 mA	5SV3311-6KL	—	—	—	—
RCCB · 2P · 25 A · 30 mA	5SV3322-3KK60, 5SV5312-6	18280	—	187366	—
RCCB · 2P · 25 A · 100 mA	5SV3412-6KL	—	—	235425	—
RCCB · 2P · 25 A · 300 mA	—	—	—	235426	—
RCCB · 2P · 40 A · 30 mA	5SV3314-6LA01, 5SV3324-4KK60, 5SV3324-3KK60, 5SM2322-3	—	—	PFIM-40/2/003-A-MW, PFIM-40/2/003-G/A, 187367	—
RCCB · 2P · 40 A · 100 mA	—	—	—	235428	—
RCCB · 2P · 40 A · 300 mA	5SM2623-8, 5SM2623-6	A9Z25240	—	235429	—
RCCB · 2P · 40 A · 1000 mA	5SM2822-8	—	—	—	—
RCCB · 2P · 63 A · 30 mA	5SV5316-6, 5SV3316-6KL, 5SV3326-4, 5SM2325-3	A9R08263, 3303430190080	—	235431, PFIM-63/2/003-G/A	—
RCCB · 2P · 63 A · 300 mA	5SM2626-8, 5SV5616-6, 5SV3616-8KL	—	—	—	—
RCCB · 2P · 80 A · 30 mA	5SV3317-6KL, 5SV3327-4KK60	—	—	—	—
RCCB · 2P · 80 A · 100 mA	5SV3417-6KL	—	—	—	—
RCCB · 2P · 100 A · 300 mA	5SM3618-6KK	—	—	—	—
RCCB · 2P · 125 A · 30 mA	5SM3315-6KK	—	—	FRCMM-125/2/003-G/A	—
RCCB · 2P · 125 A · 300 mA	5SM3615-6KK	A9N18556	—	FRCMM-125/2/03-G/A	—
RCCB · 2P · type A · 16 A · 10 mA	5SV3111-6	—	—	—	—
RCCB · 2P · type A · 16 A · 30 mA	5SV3311-6, 5SU1324-6FM16	—	—	—	—
RCCB · 2P · type A · 20 A · 30 mA	5SU1324-6FM20, 5SU1324-7FM20	—	—	—	—
RCCB · 2P · type A · 25 A · 30 mA	5SV3312-6, 5SV3312-6KK13	A9W21225, A9W31225, A9V51225, A9TYB4225, A9V61225, A9TYBE225	—	235424	—
RCCB · 2P · type A · 25 A · 100 mA	5SV3412-6	A9W22225, A9V22225	—	—	—
RCCB · 2P · type A · 25 A · 300 mA	5SV3612-6	A9W24225, A9V54225	—	—	—
RCCB · 2P · type A · 40 A · 30 mA	5SV33146KK13, 5SV3314-6, 5SM2322-6, 5SM2322-6KK01	A9TYB4240, A9TYBE240, A9V61240	—	—	—
RCCB · 2P · type A · 40 A · 100 mA	5SV3414-6	—	—	—	—
RCCB · 2P · type A · 40 A · 300 mA	5SM2622-8, 5SM2622-6, 5SV3614-6	—	—	—	—
RCCB · 2P · type A · 63 A · 30 mA	5SM2325-6, 5SV3316-6	A9W21263, A9W31263, A9V51263, A9V61263	2CSB802101R1630, 2CSB202192R1630, 2CSB802401R1630	—	—
RCCB · 2P · type A · 63 A · 100 mA	5SV3416-6	A9V22263	—	—	—
RCCB · 2P · type A · 63 A · 300 mA	5SM2625-8, 5SM2625-6, 5SV3616-6	A9W35263, A9V65263, A9V54263, A9V25263	2CSB802101R3630, 2CSB802201R3630	—	—
RCCB · 2P · type A · 63 A · 500 mA	—	A9V26263	2CSB802101R4630	—	—
RCCB · 2P · type A · 63 A · 1000 mA	—	A9V39263, A9V29263	—	—	—
RCCB · 2P · type A · 80 A · 30 mA	5SV3317-6	—	—	—	—
RCCB · 2P · type A · 80 A · 100 mA	5SV3417-6	—	—	—	—
RCCB · 2P · type A · 80 A · 300 mA	5SV3617-6	—	—	—	—

RCCB · 2P · type A · 100 A · 30 mA	5SM2327-6	—	2CSB802401R1000	—	—
RCCB · 2P · type A · 100 A · 300 mA	5SM2627-6, 5SM2627-8	—	2CSB802101R3000, 2CSB802201R3000	—	—
RCCB · 2P · type A · 100 A · 500 mA	—	—	2CSB802101R4000	—	—
RCCB · 2P · type AC · 16 A · 30 mA	—	A9Z51216	—	—	—
RCCB · 2P · type AC · 25 A · 10 mA	—	A9Z20225	—	—	—
RCCB · 2P · type AC · 25 A · 30 mA	—	A9Z21225, A9Z51225, A9Z31225, A9Z61225	—	—	—
RCCB · 2P · type AC · 25 A · 300 mA	—	A9Z24225, A9Z64225	—	—	—
RCCB · 2P · type AC · 40 A · 30 mA	—	A9Z31240, A9Z21240, A9Z61240, A9Z51240	—	—	—
RCCB · 2P · type AC · 40 A · 100 mA	—	A9Z32240, A9Z22240	—	PFIM-40/2/01-G/A	—
RCCB · 2P · type AC · 40 A · 300 mA	—	A9Z24240, A9Z64240	—	—	—
RCCB · 2P · type AC · 63 A · 30 mA	—	A9Z21263, A9Z61263, A9Z31263	—	—	—
RCCB · 2P · type AC · 63 A · 300 mA	—	A9Z64263, A9Z24263	—	—	—
RCCB · 2P · type AC · 125 A · 30 mA	—	A9N18572	—	—	—
RCCB · 2P · type AC · 125 A · 300 mA	—	A9N18592	—	—	—
RCCB · 2P · type AC · 125 A · 1000 mA	—	A9N18557	—	—	—
RCCB · 3P · 63 A · 300 mA	5SM2636-8	3303430190141	—	—	—
RCCB · 3P · 125 A · 30 mA	—	3303430190554	—	—	—
RCCB · 3P · type A · 25 A · 30 mA	—	A9W21325, A9W31325, A9V61325, A9V51325	1653231	—	—
RCCB · 3P · type A · 25 A · 100 mA	—	A9V22325	—	—	—
RCCB · 3P · type A · 25 A · 300 mA	—	A9V54325	—	—	—
RCCB · 3P · type A · 40 A · 30 mA	5SM2332-6, 5SM2332-6KK01	A9V61340	2CSB203199R1400	—	—
RCCB · 3P · type A · 40 A · 300 mA	5SM2632-6	—	—	—	—
RCCB · 3P · type A · 63 A · 30 mA	5SM2335-6, 5SM2335-6KK01	A9W21363, A9W31363, A9V51363, A9V61363	2CSB803401R1630, 2CSB803101R1630, 2CSB203199R1630	—	BD363N
RCCB · 3P · type A · 63 A · 300 mA	5SM2635-8, 5SM2635-6	A9W35363, A9W24363, A9V65363, A9V54363, A9V25363	2CSB803201R3630, 2CSB803101R3630	—	—
RCCB · 3P · type A · 63 A · 500 mA	—	A9V26363	2CSB803101R4630	—	—
RCCB · 3P · type A · 63 A · 1000 mA	—	A9V29363, A9V39363	—	—	—
RCCB · 3P · type A · 100 A · 30 mA	—	—	2CSB803401R1000	—	—
RCCB · 3P · type A · 100 A · 300 mA	—	—	2CSB803101R3000, 2CSB803201R3000	—	—
RCCB · 3P · type A · 100 A · 500 mA	—	—	2CSB803201R4000, 2CSB803101R4000	—	—
RCCB · 3P · type AC · 25 A · 100 mA	—	—	—	136566	—
RCCB · 3P · type AC · 25 A · 300 mA	—	A9Y85325	—	—	—
RCCB · 3P · type AC · 32 A · 100 mA	—	—	—	136567	—
RCCB · 3P · type AC · 40 A · 300 mA	—	A9Y85340	—	—	—
RCCB · 3P · type AC · 125 A · 30 mA	—	A9N18575, 19039, A9N18594	—	—	—

RCCB · 3P · type AC · 125 A · 300 mA	—	A9N18558, 19044, A9N18576, A9N18595	—	—	—
RCCB · 3P · type AC · 125 A · 1000 mA	—	A9N18559	—	—	—
RCCB · 3P+N · 6 A · 30 mA	—	—	—	120657	—
RCCB · 3P+N · 6 A · 100 mA	—	—	—	120661	—
RCCB · 3P+N · 10 A · 30 mA	—	—	—	mRB6-10/3N/C/003-A	—
RCCB · 3P+N · 10 A · 100 mA	—	—	—	120662	—
RCCB · 3P+N · 13 A · 30 mA	—	—	—	mRB6-13/3N/C/003-A	—
RCCB · 3P+N · 13 A · 100 mA	—	—	—	120663	—
RCCB · 3P+N · 16 A · 30 mA	—	—	—	mRB6-16/3N/C/003-A, mRB6-16/3N/D/003-A	—
RCCB · 3P+N · 16 A · 100 mA	—	—	—	120664, mRB6-16/3N/D/01-A	—
RCCB · 3P+N · 20 A · 30 mA	—	—	—	120683	—
RCCB · 3P+N · 20 A · 100 mA	—	—	—	120679	—
RCCB · 3P+N · 25 A · 100 mA	—	—	—	120680	—
RCCB · 3P+N · 32 A · 30 mA	—	EVB3S22N4A, EVB3S22NCA	—	—	—
RCCB · 3P+N · type A · 20 A · 30 mA	—	—	—	MRB4-20/3N/C/003-A	—
RCCB · 3P+N · type A · 25 A · 30 mA	—	—	—	MRB4-25/3N/C/003-A	—
RCCB · 3P+N · type AC · 25 A · 30 mA	—	A9Y84725, A9Y80725	—	—	—
RCCB · 3P+N · type AC · 25 A · 300 mA	—	A9Y85725, A9Y81725	—	—	—
RCCB · 3P+N · type AC · 40 A · 30 mA	—	A9Y84740, A9Y80740	—	—	—
RCCB · 3P+N · type AC · 40 A · 300 mA	—	A9Y85740, A9Y81740	—	—	—
RCCB · 4P · 16 A · 100 mA	—	—	—	187413	—
RCCB · 4P · 25 A · 30 mA	5SV3342-4, 5SV3342-4KK60, 5SV3342-4KK14	—	—	PFIM-25/4/003-A-MW	—
RCCB · 4P · 25 A · 100 mA	—	—	—	235436	—
RCCB · 4P · 25 A · 300 mA	5SV5642-6, 5SV3642-4, 5SV3642-6KL	18265	—	167904, 235437	—
RCCB · 4P · 40 A · 30 mA	5SM2343-6, 5SV5344-6, 5SV3344-4KK14	A9CR8440, 18266, M9R31440, 3303430235132	—	187409	—
RCCB · 4P · 40 A · 100 mA	5SV3444-6LA01, 5SV3444-8LA, 5SV3444-6LB01	—	—	PFIM-40/4/01-A-MW, PFIM-40/4/01-S/A, 187415, 187433	—
RCCB · 4P · 40 A · 300 mA	5SV3644-6KL, 5SM2643-6	18267, M9R35440	—	235468, 167905, 167909	—
RCCB · 4P · 40 A · 500 mA	5SV3744-4	—	—	—	—
RCCB · 4P · 63 A · 20 mA	5SV3346-4	R9R35463	—	—	—
RCCB · 4P · 63 A · 30 mA	5SV3346-6KK60, 5SV3346-4KK60, 5SM2345-6KK12, 5SV3346-6LB01, 5SV5346-6, 5SV3346-6LA	—	—	—	—
RCCB · 4P · 63 A · 100 mA	—	—	—	PFIM-63/4/01-A-MW, 187434	—
RCCB · 4P · 63 A · 300 mA	5SM2646-6, 5SM2645-6KK12, 5SV3646-6KL, 5SV5646-6, 5SV3646-5KK14	—	—	PFIM-63/4/03-A-MW, 235472, 187440, 167906, 187422	—
RCCB · 4P · 80 A · 30 mA	5SV3346-6KL, 5SV3357-6, 5SV3347-6LB01	—	—	—	—

RCCB · 4P · 80 A · 300 mA	5SV3647-6KL, 5SV3657-6, 5SV3647-5	—	—	187441	—
RCCB · 4P · 100 A · 30 mA	5SV4348-0	—	—	—	—
RCCB · 4P · 100 A · 300 mA	—	A9Z24491	—	187442	—
RCCB · 4P · 100 A · 500 mA	—	—	—	102872	—
RCCB · 4P · 125 A · 30 mA	—	3303430190561	—	FRCMM-125/4/003-G/A	—
RCCB · 4P · 125 A · 300 mA	—	—	—	FRCMM-125/4/03-G/A	—
RCCB · 4P · type A · 25 A · 30 mA	5SV3352-6, 5SV3342-6, 5SV33426KK03	A9W21425, A9W31425, A9V51425, A9V61425	—	PFIM-25/4/003-A	—
RCCB · 4P · type A · 25 A · 100 mA	5SV3442-6	A9W22425, A9V22425	—	—	—
RCCB · 4P · type A · 25 A · 300 mA	5SV3642-6, 5SV36526	A9V54425	—	—	—
RCCB · 4P · type A · 25 A · 500 mA	5SV3742-6	—	—	—	—
RCCB · 4P · type A · 40 A · 30 mA	5SM2342-6, 5SV3344-6, 5SM2342-6KK01, 5SV3354-6, 5SV33446KK03	A9V61440	—	PFIM-40/4/003-A, PFIM-40/4/003-A- MW, PFIM-40/4/003-G/A-MW	—
RCCB · 4P · type A · 40 A · 100 mA	5SV3444-6	—	—	—	—
RCCB · 4P · type A · 40 A · 300 mA	5SM2642-6, 5SV36546, 5SV3644-6	—	—	PFIM-40/4/03-A-MW	—
RCCB · 4P · type A · 40 A · 500 mA	5SV3744-6	—	—	—	—
RCCB · 4P · type A · 63 A · 30 mA	5SM2345-6, 5SV3346-6, 5SM2345-6KK01, 5SV33566	A9W31463, A9W21463, A9R08463, A9V61463, A9V51463	2CSB804401R1630, 2CSB804101R1630	PFIM-63/4/003-A, PFIM-63/4/003-A- MW, PFIM-63/4/003-G/A-MW	—
RCCB · 4P · type A · 63 A · 100 mA	5SM2445-6, 5SV3446-6	A9W22463, A9V22463	—	—	—
RCCB · 4P · type A · 63 A · 300 mA	5SM2645-6, 5SV3646-6, 5SM2645-8, 5SV36566	A9W24463, A9W35463, A9V65463, A9V25463, A9V54463	2CSB804201R3630, 2CSB804101R3630	PFIM-63/4/03-A	—
RCCB · 4P · type A · 63 A · 500 mA	5SV3746-6	A9V26463	2CSB804101R4630	—	—
RCCB · 4P · type A · 63 A · 1000 mA	—	A9V39463, A9V29463	—	—	—
RCCB · 4P · type A · 80 A · 30 mA	5SV3347-6	—	—	—	—
RCCB · 4P · type A · 80 A · 100 mA	5SV34476	—	—	—	—
RCCB · 4P · type A · 80 A · 300 mA	5SV3647-6	—	—	—	—
RCCB · 4P · type A · 80 A · 500 mA	5SV3747-6	—	—	—	—
RCCB · 4P · type A · 100 A · 30 mA	5SM2347-6	—	2CSB804401R1000	PFNM-100/4/003	—
RCCB · 4P · type A · 100 A · 300 mA	5SM26476, 5SM2647-8	—	2CSB804101R3000, 2CSB804201R3000	PFNM-100/4/03-(A), PFNM-100/4/03-S/A	—
RCCB · 4P · type A · 100 A · 500 mA	—	—	2CSB804101R4000, 2CSB804201R4000	—	—
RCCB · 4P · type A · 125 A · 300 mA	—	—	2CSF204201R3950	—	—
RCCB · 4P · type A · 125 A · 500 mA	—	—	2CSF204201R4950	—	—
RCCB · 4P · type AC · 25 A · 30 mA	—	A9Z21425, A9Z51425, A9Z31425, A9Z61425	—	—	—
RCCB · 4P · type AC · 25 A · 300 mA	—	A9Z24425, A9Z64425	—	—	—
RCCB · 4P · type AC · 40 A · 30 mA	—	A9Z21440, A9Z51440, A9Z31440, A9Z61440	—	—	—
RCCB · 4P · type AC · 40 A · 100 mA	—	A9Z22440, A9Z32440, A9Z83440	—	—	—
RCCB · 4P · type AC · 40 A · 300 mA	—	A9Z64440, A9Z24440, A9Z25440, A9Z35440, A9Z65440	—	—	—

RCCB · 4P · type AC · 40 A · 500 mA	—	A9Z66440, A9Z26440	—	—	—
RCCB · 4P · type AC · 63 A · 30 mA	—	A9Z21463, A9Z31463, A9Z51463, A9Z61463, 19015	—	—	—
RCCB · 4P · type AC · 63 A · 100 mA	—	A9Z32463, A9Z22463, A9Z83463	—	PFIM-63/4/01-S/A, PFIM-63/4/01-G/A	—
RCCB · 4P · type AC · 63 A · 300 mA	—	A9Z35463, A9Z24463, A9Z64463, A9Z25463, 19016, A9Z65463	—	—	—
RCCB · 4P · type AC · 63 A · 500 mA	—	A9Z66463, A9Z26463	—	—	—
RCCB · 4P · type AC · 80 A · 30 mA	—	A9Z21480, A9Z61480	—	—	—
RCCB · 4P · type AC · 80 A · 300 mA	—	A9Z35480, A9Z64480, A9Z65480, A9Z25480, A9Z24480	—	PFIM-80/4/03-S/A	—
RCCB · 4P · type AC · 80 A · 500 mA	—	A9Z66480	—	—	—
RCCB · 4P · type AC · 100 A · 30 mA	—	A9Z21491	—	—	—
RCCB · 4P · type AC · 100 A · 100 mA	—	A9Z32491, A9Z22491	—	—	—
RCCB · 4P · type AC · 100 A · 300 mA	—	A9Z25491	—	—	—
RCCB · 4P · type AC · 125 A · 30 mA	—	A9N18597	—	—	—
RCCB · 4P · type AC · 125 A · 300 mA	—	19042, A9N18560, A9N18579, A9N18598	—	—	—
RCCB · 4P · type AC · 125 A · 500 mA	—	A9N18599, A9N18588, A9N18580	—	—	—
RCCB · 4P · type AC · 125 A · 1000 mA	—	A9N18561, A9N18589	—	—	—
RCCB · 4P · type B · 25 A · 30 mA	—	—	—	167880	—
RCCB · 4P · type B · 25 A · 300 mA	—	—	—	FRCDM-25/4/03-G/B+, 167896, 167888	—
RCCB · 4P · type B · 40 A · 30 mA	—	—	—	167881	—
RCCB · 4P · type B · 40 A · 300 mA	—	—	—	FRCDM-40/4/03-G/B, 167901, 167889, 167885	—
RCCB · 4P · type B · 63 A · 30 mA	—	—	—	167894, FRCDM-63/4/003-G/B+	—
RCCB · 4P · type B · 63 A · 300 mA	—	—	—	FRCDM-63/4/03-G/B, FRCDM-63/4/03-S/B+	—

Part numbers and designations are those of the original manufacturers and are given for identification. cBallast is an independent supplier. © cBallast 2026 · cballast.com