

Specifications



Photo is representative

Eaton 104555

Eaton xEffect SASY 60i Enclosures Switch- & Controlgear Enclosure. Busbar adapter, 3p, for NZM2, 250A, UL508

General specifications

PRODUCT NAME	Eaton xEffect SASY 60i MCCB adapter
CATALOG NUMBER	104555
MODEL CODE	NZM2-XAD250
EAN	4015081043736
PRODUCT LENGTH/DEPTH	192 mm
PRODUCT HEIGHT	35 mm
PRODUCT WIDTH	106 mm
PRODUCT WEIGHT	0.828 kg
COMPLIANCES	CE marking CSA-C22.2 No. 14 IEC 60439-1 UL CSA09 (refer to approbation report) UL508A RoHS conform
CERTIFICATIONS	UL (File No. E300273) North America (UL listed, CSA certified) CSA (Class No. 3211-37) CSA (File No. 236217) UL (Category Control Number NMTR, NMTR7)



Powering Business Worldwide

Additional information

FEATURES	Self-extinguishing acc. UL 94
FUNCTIONS	Busbar adapters for NZM Current limiting circuit breaker, refer to approbation report Component adapter for circuit breakers and switch-disconnector
SUITABLE FOR	Surface mounting on flat copper busbars 12 – 30 x 5 – 10, double T and triple T profile
USED WITH	N(S)2 PN2, Feeder circuits NZM2 Busbar adapters for NZM Compact system 60 mm system

Design verification to IEC/EN 61439 - technical data

EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID	10 W
TEMPERATURE RESISTANCE	Up to 120 °C

Technical data - mechanical

ADAPTER WIDTH	106 mm
BUSBAR ADAPTER WIDTH	106 mm
BUSBAR DISTANCE	60 mm
BUSBAR THICKNESS - MAX	10 mm
BUSBAR THICKNESS - MIN	5 mm
DEGREE OF PROTECTION	Feeder circuits
MOUNTING RAIL ARMAMENT	None
RAIL WIDTH	30 mm

Delivery programme

NOMINAL CURRENT	250 A
NUMBER OF POLES	Three-pole
TYPE	• 60 mm system • Busbar adapters for NZM • Compact system

Technical data - electrical

CREEPAGE RESISTANCE	CTI 200
ELECTRIC CONNECTION TYPE	Other
RATED OPERATION CURRENT (IE)	250 A
VOLTAGE RATING (UL CSA 13)	Max. 600 V AC
VOLTAGE RATING AT AC	690 V AC

Resources

BROCHURES	eaton-xeffect-sasy60i-customer-success-story-css-wagner-mueller-en-us.pdf
CERTIFICATION REPORTS	eaton-xeffect-sasy-60i-declaration-of-conformity.pdf
DRAWINGS	eaton-circuit-breaker-xeffect-sasy-busbar-adapter-dimensions.eps eaton-circuit-breaker-xeffect-sasy-busbar-adapter-3d-drawing.eps
INSTALLATION INSTRUCTIONS	IL01502145Z
MCAD MODEL	nzm2_xad250.stp

[eaton-busbar-adapters-
mcad-drawings-nzm2-
xad250.dwg](#)

TECHNICAL DATA SHEETS

[eaton-xeffect-sasy-60i-
fk4300-1167gb-en-us.pdf](#)

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



Eaton Corporation plc Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2026 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

