

Specifications



Eaton 121080

Eaton Moeller series xComfort - Actuators. Switching device, potential-free, 8 A, 230 VAC. Push-button function in Basic Mode

General specifications

PRODUCT NAME	Eaton Moeller series xComfort switching actuator
CATALOG NUMBER	121080
MODEL CODE	CSAU-01/04
EAN	4015081189106
PRODUCT LENGTH/DEPTH	65 mm
PRODUCT HEIGHT	27 mm
PRODUCT WIDTH	65 mm
PRODUCT WEIGHT	0.056 kg
COMPLIANCES	RoHS conform

Product specifications

FEATURES	Radio frequent bidirectional Local operation/hand operation
BUS SYSTEM OPERATING TYPE	Radio frequent xComfort
ACTUATION FUNCTION	Switching
BUS SYSTEM PRODUCT TYPE	Actuator
BUILT-IN INSTALLATION BOX DEPTH - MIN	26 mm
NUMBER OF INPUTS (BINARY)	0
NUMBER OF SWITCHING CONTACTS - MAX	1
AMPERAGE RATING	0 A
FITTED WITH:	Bus connection
SWITCHING CURRENT - MAX	8 A
SWITCHING POWER - MAX	1840 W
WIDTH IN NUMBER OF MODULAR SPACINGS	3
OUTPUT POWER	1840 W
POWER SUPPLY	Mains
DEGREE OF PROTECTION	IP20
FUNCTIONS	Bus module detachable
MOUNTING METHOD	Flush mounting Flush mounted (plaster)
POWER CONSUMPTION	0.6 W
NUMBER OF LINKABLE DEVICES	32

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:

Resources

DECLARATIONS OF CONFORMITY	eaton-switching-actuator-declaration-of-conformity-eu250183en.pdf
DRAWINGS	eaton-xcomfort-xcomfort-sensor-dimensions-008.jpg
INSTALLATION INSTRUCTIONS	ma136211063_2018_02.pdf
INSTALLATION VIDEOS	xComfort Sensors and Actuators Video EN-US
	xComfort - Pairing multiple switches with multiple actuators EN
	xComfort - Un-pairing a switch from an actuator EN
	Pairing one switch to one actuator
	xComfort - Pairing one switch with multiple actuators EN
	Pairing two or more switches to one actuator
MANUALS AND USER GUIDES	xComfort - Pairing a double switch with two actuators EN
	DA-MN-136211063
WIRING DIAGRAMS	eaton-wiring-diagram-csau_01_02.jpg



Eaton Corporation plc Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2026 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

