


Specifications



Eaton 184127

Eaton Moeller series IZMX/INX - ACB. Eaton Moeller series IZMX/INX - ACB. Reset remote, 220-240VAC/DC, EMEA

General specifications

PRODUCT NAME	Eaton Moeller series IZMX/INX remote reset
CATALOG NUMBER	184127
MODEL CODE	IZMX-RR230AD-40-1
EAN	4015081783250
PRODUCT LENGTH/DEPTH	150 mm
PRODUCT HEIGHT	100 mm
PRODUCT WIDTH	100 mm
PRODUCT WEIGHT	0.125 kg
COMPLIANCES	RoHS conform

Additional information

ACCESSORY/SPARE PART TYPE	Trip indication / Reset options
----------------------------------	---------------------------------

Delivery programme

SPECIAL FEATURES

- The circuit-breaker is equipped with a mechanical trip indicator (red pin).
- After the remote reset coil is electrically actuated, the reclosing lockout can be reset.
- Cannot be combined with remote reset.
- The retrofit kit includes the required SEC control cable terminals.

SUITABLE FOR	Overload relay Motor safety switch Off-load switch Power circuit breaker
TYPE	Accessory
USED WITH	IZMX40...F IZMX40...W

Design verification to IEC/EN 61439 - technical data

AMBIENT OPERATING TEMPERATURE - MAX	70 °C
--	-------

AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
--	--------

Technical data - electrical

ADJUSTMENT RANGE UNDELAYED SHORT-CIRCUIT RELEASE (END VALUE) - MAX	0 A
CONTROL VOLTAGE OPERATING RANGE	208 - 240 V AC (50/60 Hz) 208 - 250 V DC
ELECTRIC CONNECTION TYPE	Flat plug-in connection
INITIAL VALUE OF THE UNDELAYED SHORT-CIRCUIT RELEASE - MIN	0 A
POWER CONSUMPTION	500 VA/W AC/DC
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX	240 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	208 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	240 V
RATED CONTROL SUPPLY	208 V

VOLTAGE (US) AT AC, 60 HZ - MIN

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	250 V
---	-------

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	220 V
---	-------

VOLTAGE TYPE	AC/DC
--------------	-------

Technical data - mechanical

NUMBER OF CONTACTS (CHANGE-OVER CONTACTS)	0
---	---

NUMBER OF CONTACTS (NORMALLY CLOSED CONTACTS)	0
---	---

NUMBER OF CONTACTS (NORMALLY OPEN CONTACTS)	0
---	---

Resources

CATALOGUES	eaton-acb-izm63-catalog-ca0135003en-en-us.pdf
------------	---

ECAD MODEL	DA-CE-ETN.IZMX-RR230AD-40-1
------------	---

INSTALLATION INSTRUCTIONS	eaton-izmx16-izmx40-pop-out-trip-indicators-il0131126en-us.pdf
---------------------------	--

INSTALLATION VIDEOS	Air Circuit Breakers Series IZMX
---------------------	--

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



Eaton Corporation plc Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2026 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

