

# Specifications



Photo is representative



## Eaton 191491

Eaton Moeller series NZM - Molded Case Circuit Breaker. NZM3 PXR20 circuit breaker, 400A, 4p, variable, screw terminal, N, 3

### General specifications

|                             |                                                                 |
|-----------------------------|-----------------------------------------------------------------|
| <b>PRODUCT NAME</b>         | Eaton Moeller series NZM molded case circuit breaker electronic |
| <b>CATALOG NUMBER</b>       | 191491                                                          |
| <b>MODEL CODE</b>           | NZMN3-4-VX400/VAR                                               |
| <b>EAN</b>                  | 4015081920037                                                   |
| <b>PRODUCT LENGTH/DEPTH</b> | 166 mm                                                          |
| <b>PRODUCT HEIGHT</b>       | 275 mm                                                          |
| <b>PRODUCT WIDTH</b>        | 185 mm                                                          |
| <b>PRODUCT WEIGHT</b>       | 8.4 kg                                                          |
| <b>COMPLIANCES</b>          | RoHS conform                                                    |
| <b>CERTIFICATIONS</b>       | IEC/EN 60947<br>IEC                                             |

## Additional information

### FUNCTIONS

Systems, cable, selectivity  
and generator protection

## Delivery programme

**AMPERAGE RATING** 400 A

**APPLICATION** Use in unearthed supply  
systems at 690 V

**CIRCUIT BREAKER FRAME  
TYPE** NZM3

**FEATURES** Motor drive optional  
Protection unit

**NUMBER OF POLES** Four-pole

**RELEASE SYSTEM** Electronic release

### SPECIAL FEATURES

- LSI overload protection and delayed and non-delayed short-circuit protective device
- R.m.s. value measurement and "thermal memory"
- USB interface for configuration and test function with Power Xpert Protection Manager software
- Optionally communication-capable with interface module and internal Modbus RTU module or CAM
- Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit breaker (Rated short-circuit breaking capacity  $I_{cn}$ )
- Rated current = rated uninterrupted current: 400 A
- Terminal capacity hint: Up to 240 mm<sup>2</sup> can be connected depending on the cable manufacturer.

|             |                 |
|-------------|-----------------|
| <b>TYPE</b> | Circuit breaker |
|-------------|-----------------|

## Design verification to IEC/EN 61439

|                                                                                         |                                                                                                                                  |
|-----------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------|
| <b>10.10 TEMPERATURE RISE</b>                                                           | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| <b>10.11 SHORT-CIRCUIT RATING</b>                                                       | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| <b>10.12 ELECTROMAGNETIC COMPATIBILITY</b>                                              | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| <b>10.13 MECHANICAL FUNCTION</b>                                                        | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.                         |
| <b>10.2.2 CORROSION RESISTANCE</b>                                                      | Meets the product standard's requirements.                                                                                       |
| <b>10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES</b>                         | Meets the product standard's requirements.                                                                                       |
| <b>10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT</b>       | Meets the product standard's requirements.                                                                                       |
| <b>10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS</b> | Meets the product standard's requirements.                                                                                       |
| <b>10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION</b>                                 | Meets the product standard's requirements.                                                                                       |
| <b>10.2.5 LIFTING</b>                                                                   | Does not apply, since the entire switchgear needs to be evaluated.                                                               |
| <b>10.2.6 MECHANICAL IMPACT</b>                                                         | Does not apply, since the entire switchgear needs to be evaluated.                                                               |
| <b>10.2.7 INSCRIPTIONS</b>                                                              | Meets the product standard's requirements.                                                                                       |
| <b>10.3 DEGREE OF PROTECTION OF ASSEMBLIES</b>                                          | Does not apply, since the entire switchgear needs to be evaluated.                                                               |
| <b>10.4 CLEARANCES AND CREEPAGE DISTANCES</b>                                           | Meets the product standard's requirements.                                                                                       |
| <b>10.5 PROTECTION</b>                                                                  | Does not apply, since the                                                                                                        |

## Design verification to IEC/EN 61439 - technical data

|                                                                      |        |
|----------------------------------------------------------------------|--------|
| <b>AMBIENT OPERATING TEMPERATURE - MAX</b>                           | 70 °C  |
| <b>AMBIENT STORAGE TEMPERATURE - MAX</b>                             | 70 °C  |
| <b>AMBIENT OPERATING TEMPERATURE - MIN</b>                           | -25 °C |
| <b>AMBIENT STORAGE TEMPERATURE - MIN</b>                             | 40 °C  |
| <b>EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT</b>                 | 48 W   |
| <b>RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)</b> | 400 A  |

|                                                                 |                                                                    |
|-----------------------------------------------------------------|--------------------------------------------------------------------|
| <b>AGAINST ELECTRIC SHOCK</b>                                   | entire switchgear needs to be evaluated.                           |
| <b>10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS</b>   | Does not apply, since the entire switchgear needs to be evaluated. |
| <b>10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS</b>        | Is the panel builder's responsibility.                             |
| <b>10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS</b>                 | Is the panel builder's responsibility.                             |
| <b>10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH</b>                 | Is the panel builder's responsibility.                             |
| <b>10.9.3 IMPULSE WITHSTAND VOLTAGE</b>                         | Is the panel builder's responsibility.                             |
| <b>10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL</b> | Is the panel builder's responsibility.                             |

## Technical data - electrical

|                                                                                    |                                                                                                      |
|------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------|
| <b>AMPERAGE RATING</b>                                                             | 400 A                                                                                                |
| <b>CURRENT RATING OF NEUTRAL CONDUCTOR</b>                                         | 0 - 60% - 100% of phase conductor                                                                    |
| <b>DIRECTION OF INCOMING SUPPLY</b>                                                | As required                                                                                          |
| <b>ELECTRICAL CONNECTION TYPE OF MAIN CIRCUIT</b>                                  | Screw connection                                                                                     |
| <b>HANDLE TYPE</b>                                                                 | Rocker lever                                                                                         |
| <b>INSTANTANEOUS CURRENT SETTING (II) - MAX</b>                                    | 12 A                                                                                                 |
| <b>INSTANTANEOUS CURRENT SETTING (II) - MIN</b>                                    | 2 A                                                                                                  |
| <b>ISOLATION</b>                                                                   | 500 V AC (between auxiliary contacts and main contacts)<br>300 V AC (between the auxiliary contacts) |
| <b>LIFESPAN, ELECTRICAL</b>                                                        | 3000 operations at 690 V AC-1<br>5000 operations at 415 V AC-1<br>5000 operations at 400 V AC-1      |
| <b>NUMBER OF OPERATIONS PER HOUR - MAX</b>                                         | 60                                                                                                   |
| <b>OVERLOAD CURRENT SETTING (IR) - MAX</b>                                         | 400 A                                                                                                |
| <b>OVERLOAD CURRENT SETTING (IR) - MIN</b>                                         | 160 A                                                                                                |
| <b>OVERVOLTAGE CATEGORY</b>                                                        | III                                                                                                  |
| <b>POLLUTION DEGREE</b>                                                            | 3                                                                                                    |
| <b>RATED IMPULSE WITHSTAND VOLTAGE (UIMP) AT AUXILIARY CONTACTS</b>                | 6000 V                                                                                               |
| <b>RATED IMPULSE WITHSTAND VOLTAGE (UIMP) AT MAIN CONTACTS</b>                     | 8000 V                                                                                               |
| <b>RATED INSULATION VOLTAGE (UI)</b>                                               | 690 V AC                                                                                             |
| <b>RATED SHORT-CIRCUIT BREAKING CAPACITY ICS (IEC/EN 60947) AT 230 V, 50/60 HZ</b> | 85 kA                                                                                                |

## Technical data - mechanical

|                                                                |                                                                                                                                                                                                                                                                                |
|----------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>CLIMATIC PROOFING</b>                                       | Damp heat, constant, to IEC 60068-2-78<br>Damp heat, cyclic, to IEC 60068-2-30                                                                                                                                                                                                 |
| <b>DEGREE OF PROTECTION</b>                                    | IP20<br>IP20 (basic degree of protection, in the operating controls area)                                                                                                                                                                                                      |
| <b>DEGREE OF PROTECTION (IP), FRONT SIDE</b>                   | IP40 (with insulating surround)<br>IP66 (with door coupling rotary handle)                                                                                                                                                                                                     |
| <b>DEGREE OF PROTECTION (TERMINATIONS)</b>                     | IP00 (terminations, phase isolator and strip terminal)<br>IP10 (tunnel terminal)                                                                                                                                                                                               |
| <b>LIFESPAN, MECHANICAL</b>                                    | 15000 operations                                                                                                                                                                                                                                                               |
| <b>MOUNTING METHOD</b>                                         | Fixed<br>Built-in device fixed built-in technique                                                                                                                                                                                                                              |
| <b>NUMBER OF AUXILIARY CONTACTS (CHANGE-OVER CONTACTS)</b>     | 0                                                                                                                                                                                                                                                                              |
| <b>NUMBER OF AUXILIARY CONTACTS (NORMALLY CLOSED CONTACTS)</b> | 0                                                                                                                                                                                                                                                                              |
| <b>NUMBER OF AUXILIARY CONTACTS (NORMALLY OPEN CONTACTS)</b>   | 0                                                                                                                                                                                                                                                                              |
| <b>POSITION OF CONNECTION FOR MAIN CURRENT CIRCUIT</b>         | Front side                                                                                                                                                                                                                                                                     |
| <b>PROTECTION AGAINST DIRECT CONTACT</b>                       | Finger and back-of-hand proof to DIN EN 50274/VDE 0106 part 110                                                                                                                                                                                                                |
| <b>SHOCK RESISTANCE</b>                                        | 20 g (half-sinusoidal shock 20 ms)                                                                                                                                                                                                                                             |
| <b>SPECIAL FEATURES</b>                                        | <ul style="list-style-type: none"> <li>• LSI overload protection and delayed and non-delayed short-circuit protective device</li> <li>• R.m.s. value measurement and "thermal memory"</li> <li>• USB interface for configuration and test function with Power Xpert</li> </ul> |

|                                                                                                    |         |
|----------------------------------------------------------------------------------------------------|---------|
| <b>RATED SHORT-CIRCUIT<br/>BREAKING CAPACITY ICS<br/>(IEC/EN 60947) AT<br/>400/415 V, 50/60 HZ</b> | 50 kA   |
| <b>RATED SHORT-CIRCUIT<br/>BREAKING CAPACITY ICS<br/>(IEC/EN 60947) AT 440 V,<br/>50/60 HZ</b>     | 35 kA   |
| <b>RATED SHORT-CIRCUIT<br/>BREAKING CAPACITY ICS<br/>(IEC/EN 60947) AT 525 V,<br/>50/60 HZ</b>     | 13 kA   |
| <b>RATED SHORT-CIRCUIT<br/>BREAKING CAPACITY ICS<br/>(IEC/EN 60947) AT 690 V,<br/>50/60 HZ</b>     | 5 kA    |
| <b>RATED SHORT-CIRCUIT<br/>MAKING CAPACITY ICM<br/>AT 240 V, 50/60 HZ</b>                          | 187 kA  |
| <b>RATED SHORT-CIRCUIT<br/>MAKING CAPACITY ICM<br/>AT 400/415 V, 50/60 HZ</b>                      | 110 kA  |
| <b>RATED SHORT-CIRCUIT<br/>MAKING CAPACITY ICM<br/>AT 440 V, 50/60 HZ</b>                          | 77 kA   |
| <b>RATED SHORT-CIRCUIT<br/>MAKING CAPACITY ICM<br/>AT 525 V, 50/60 HZ</b>                          | 55 kA   |
| <b>RATED SHORT-CIRCUIT<br/>MAKING CAPACITY ICM<br/>AT 690 V, 50/60 HZ</b>                          | 40 kA   |
| <b>RATED SHORT-TIME<br/>WITHSTAND CURRENT (T<br/>= 0.3 S)</b>                                      | 3.3 kA  |
| <b>RATED SHORT-TIME<br/>WITHSTAND CURRENT (T<br/>= 1 S)</b>                                        | 3.3 kA  |
| <b>SHORT DELAY CURRENT<br/>SETTING (ISD) - MAX</b>                                                 | 10 A    |
| <b>SHORT DELAY CURRENT<br/>SETTING (ISD) - MIN</b>                                                 | 2 A     |
| <b>SHORT-CIRCUIT RELEASE<br/>DELAYED SETTING - MAX</b>                                             | 4000 A  |
| <b>SHORT-CIRCUIT RELEASE<br/>DELAYED SETTING - MIN</b>                                             | 320 A   |
| <b>SHORT-CIRCUIT RELEASE<br/>NON-DELAYED SETTING -<br/>MAX</b>                                     | 4800 A  |
| <b>SHORT-CIRCUIT RELEASE<br/>NON-DELAYED SETTING -<br/>MIN</b>                                     | 800 A   |
| <b>SHORT-CIRCUIT TOTAL<br/>BREAKTIME</b>                                                           | < 10 ms |

- 
- Protection Manager software
- Optionally communication-capable with interface module and internal Modbus RTU module or CAM
  - Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit breaker (Rated short-circuit breaking capacity I<sub>cn</sub>)
  - Rated current = rated uninterrupted current: 400 A
  - Terminal capacity hint: Up to 240 mm<sup>2</sup> can be connected depending on the cable manufacturer.
-

|                      |                    |
|----------------------|--------------------|
| UTILIZATION CATEGORY | A (IEC/EN 60947-2) |
| VOLTAGE RATING       | 690 V - 690 V      |

## Technical data - mechanical - terminals

|                                                              |                                                                                                                                                                                                                                                                                                                                                                                         |
|--------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>OPTIONAL TERMINALS</b>                                    | Box terminal. Connection on rear. Tunnel terminal                                                                                                                                                                                                                                                                                                                                       |
| <b>STANDARD TERMINALS</b>                                    | Screw terminal                                                                                                                                                                                                                                                                                                                                                                          |
| <b>TERMINAL CAPACITY (ALUMINUM SOLID CONDUCTOR/CABLE)</b>    | 16 mm <sup>2</sup> (1x) at tunnel terminal                                                                                                                                                                                                                                                                                                                                              |
| <b>TERMINAL CAPACITY (ALUMINUM STRANDED CONDUCTOR/CABLE)</b> | 50 mm <sup>2</sup> - 240 mm <sup>2</sup> (1x) at 2-hole tunnel terminal<br>25 mm <sup>2</sup> - 185 mm <sup>2</sup> (1x) at tunnel terminal<br>50 mm <sup>2</sup> - 240 mm <sup>2</sup> (2x) at 2-hole tunnel terminal                                                                                                                                                                  |
| <b>TERMINAL CAPACITY (CONTROL CABLE)</b>                     | 0.75 mm <sup>2</sup> - 2.5 mm <sup>2</sup> (1x)<br>0.75 mm <sup>2</sup> - 1.5 mm <sup>2</sup> (2x)                                                                                                                                                                                                                                                                                      |
| <b>TERMINAL CAPACITY (COPPER BUSBAR)</b>                     | Min. 20 mm x 5 mm direct at switch rear-side connection<br>Max. 30 mm x 10 mm + 30 mm x 5 mm direct at switch rear-side connection<br>M10 at rear-side screw connection<br>Max. 10 mm x 50 mm (2x) at rear-side width extension                                                                                                                                                         |
| <b>TERMINAL CAPACITY (COPPER SOLID CONDUCTOR/CABLE)</b>      | 16 mm <sup>2</sup> (1x) at tunnel terminal<br>16 mm <sup>2</sup> (2x) direct at switch rear-side connection<br>16 mm <sup>2</sup> (1x) direct at switch rear-side connection<br>16 mm <sup>2</sup> (2x) at box terminal<br>300 mm <sup>2</sup> (2x) at rear-side width extension                                                                                                        |
| <b>TERMINAL CAPACITY (COPPER STRANDED CONDUCTOR/CABLE)</b>   | 35 mm <sup>2</sup> - 240 mm <sup>2</sup> (1x) at box terminal<br>25 mm <sup>2</sup> - 240 mm <sup>2</sup> (2x) direct at switch rear-side connection<br>25 mm <sup>2</sup> - 120 mm <sup>2</sup> (2x) at box terminal<br>25 mm <sup>2</sup> - 240 mm <sup>2</sup> (1x) direct at switch rear-side connection<br>16 mm <sup>2</sup> - 185 mm <sup>2</sup> (1x) at 1-hole tunnel terminal |
| <b>TERMINAL CAPACITY (COPPER STRIP)</b>                      | Max. 10 segments of 32 mm x 1 mm + 5 segments of 32 mm x 1 mm at rear-side connection (punched)                                                                                                                                                                                                                                                                                         |

## Resources

|                                   |                                                                                                                                                                |
|-----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>BROCHURES</b>                  | <a href="#">eaton-digital-nzm-brochure-br013003en-en-us.pdf</a><br><br><a href="#">eaton-feerum-the-whole-grain-solution-success-story-en-us.pdf</a>           |
| <b>CATALOGUES</b>                 | <a href="#">eaton-digital-nzm-catalog-ca013003en-en-us.pdf</a>                                                                                                 |
| <b>CHARACTERISTIC CURVE</b>       | <a href="#">eaton-circuit-breaker-nzm-mccb-characteristic-curve-011.eps</a><br><br><a href="#">eaton-circuit-breaker-nzm-mccb-characteristic-curve-015.eps</a> |
| <b>DECLARATIONS OF CONFORMITY</b> | <a href="#">eaton-molded-case-circuit-breaker-declaration-of-conformity-eu250293en.pdf</a>                                                                     |
| <b>DRAWINGS</b>                   | <a href="#">eaton-circuit-breaker-switch-nzm-mccb-dimensions-016.eps</a><br><br><a href="#">eaton-circuit-breaker-nzm-mccb-dimensions-021.eps</a>              |
| <b>INSTALLATION INSTRUCTIONS</b>  | <a href="#">eaton-circuit-breaker-basic-unit-bg3-il012100zu.pdf</a>                                                                                            |
| <b>INSTALLATION VIDEOS</b>        | <a href="#">The new digital NZM Range</a><br><br><a href="#">Introduction of the new digital circuit breaker NZM</a>                                           |
| <b>MCAD MODEL</b>                 | <a href="#">eaton-molded-case-switches-mcad-3d-models-nzm3-4p.stp</a><br><br><a href="#">eaton-molded-case-switches-mcad-drawings-nzm3-4p.dwg</a>              |
| <b>PEP ECO-PASSPORT</b>           | <a href="#">eaton-molded-case-switches-pep-eato-00251-v0101-en.pdf</a>                                                                                         |
| <b>TECHNICAL DATA SHEETS</b>      | <a href="#">eaton-nzm-technical-information-sheet</a>                                                                                                          |

---

Min. 6 segments of 16 mm  
x 0.8 mm at rear-side  
connection (punched)  
Max. 10 segments of 24  
mm x 1 mm + 5 segments  
of 24 mm x 1 mm  
Min. 6 segments of 16 mm  
x 0.8 mm at box terminal  
10 segments of 50 mm x 1  
mm (2x) at rear-side width  
extension  
Max. 8 segments of 24  
mm x 1 mm (2x) at box  
terminal

---

---

**PROJECT NAME:**

---

**PROJECT NUMBER:**

---

**PREPARED BY:**

---

**DATE:**

---



**Eaton Corporation plc** Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2026 Eaton. All Rights Reserved.

Follow us on social media to get the  
latest product and support  
information.

