



Digital Multimeter, Auto-Ranging, 1000V



The Klein Tools MM600 Multimeter is an automatically ranging digital multimeter that measures AC/DC voltage, AC/DC current, and resistance. It can also measure temperature, capacitance, frequency, duty-cycle, test diodes and continuity. Exclusively designed from the ground up by electricians for electricians. Years of field research, combined with extensive input from electricians across America, inspired the development of meters loaded with innovative, time-saving features.

Specifications

Batteries:	2 x AAA	Drop Protection:	6.6' (2 m)
Display:	4000 Count LCD	Functions:	Measures up to 1000V AC/DC voltage, 10A AC/DC current and 40M Ω resistance plus temperature, capacitance, frequency, duty-cycle, test diodes and continuity
Voltage:	1000V AC; 1000 V DC	Frequency:	1Hz - 500 KHz
Current:	10A AC; 10A DC	Capacitance:	1000 μ F
Ohms (Resistance):	40MO	Ingress Protection:	IP42
Standard:	CAT IV 600V; CAT III 1000V	Temperature Range:	0° - 1000°F (-18° - 538°C)
Included:	Carrying Case, Test Leads, Thermocouple, Batteries, and User Manual	Overall Length (Inch):	7
Overall Length (cm):	17.8	Overall Height (Inch):	2.09
Overall Height (cm):	5.3	Overall Width (Inch):	3.55
Overall Width (cm):	9	Weight (oz):	14.4
Weight (g):	408		